

# REST API 1.11

This guide describes how to use the Pure Storage REST API. The guide is divided into two sections: Overview and Resources. The Overview section describes high-level concepts while the Resources section contains a comprehensive list of resources and endpoints.

- [Overview](#)
- [Release Notes](#)
- [Resources](#)

## REST API Overview

The Pure Storage REST API provides simple interfaces for many Purity commands.

### What is REST?

REpresentational State Transfer (REST) uses HTTP requests to interact with resources within Pure Storage. REST is an architectural style that describes the following constraints:

- **Uniform Interface.** Individual resources are identified in requests using URIs as resource identifiers. For example:

```
volume
volume/v1
```

Clients manipulate resources through request methods, such as:

| Method | Description        | Example          |
|--------|--------------------|------------------|
| GET    | List resources.    | GET volume       |
| POST   | Create a resource. | POST volume/v1   |
| PUT    | Modify a resource. | PUT volume/v1    |
| DELETE | Delete a resource. | DELETE volume/v1 |

Requests can include additional parameters, either in the URL or as JSON post data. For example, the snap parameter is included in the following request to list all snapshots:

```
GET volume?snap=true
```

Responses return a response code and data (represented in JSON). For example, the following GET volume/v1 request returns a response code 200 OK and the attribute details for a volume named "v1":

```
>> GET volume/v1
<< 200 OK
{
  "created": "Tue Jan 28 06:15:23 2014",
  "name": "v1",
  "serial": "CEE061D3B3B23499000101E1",
  "size": 1073741824,
  "source": null
}
```

- **Stateless.** The necessary state to handle a request is contained in the request itself.
- **Cacheable.** The responses must implicitly or explicitly define themselves as cacheable.
- **Client-Server.** The uniform interface creates separation between client and server. Clients can be more portable, servers do not need to know anything about user interface or state.
- **Layered System.** A client cannot tell if it is connected directly to the server; intermediary servers can be used to improve scalability or enforce security policies.

## Pure Storage REST API

The Pure Storage REST API provides simple interfaces for many Purity commands.

In the following example, the Purity CLI command

returns the attributes for the array:

```
$ purearray list
Name      ID                               Version  Revision
pure-001  9d2c3325-c5b9-14ad-43b8-1c773a6406b90  4.8.0    201510290821+a1af0ba
```

The equivalent REST API request GET `https://pure-001.example.com/api/1.11/array` produces the same results:

```
>> GET https://pure-001.example.com/api/1.11/array
<< 200 OK

{
  "array_name": "pure-001",
  "id": "9d2c3325-c5b9-14ad-43b8-1c773a6406b9",
  "revision": "201510290821+a1af0ba",
  "version": "4.8.0"
}
```

Using the REST API consists of the following steps:

1. Generate the API token. This is a one-time step.
2. Create the REST session.
3. Submit REST API requests.
4. Invalidate the REST session.

## Generating an API Token

The REST API uses [authentication](#) tokens to create sessions. All Purity users can generate their own API tokens.

Generate the API token through the Purity GUI (System > Users > Create API Token) or CLI (`pureadmin create --api-token`).

API tokens can also be generated through the [REST API](#). Generating API tokens through the REST API may be convenient during development, but is discouraged in production environments as it exposes usernames and passwords.

Once generated, the API token is valid until it is deleted or recreated.

## Creating a REST Session

After the API token has been generated, use the token to create a REST session.

To create a REST session, send the following request and payload:

```
>> POST https://pure-001.example.com/api/1.11/auth/session
<< 200 OK

{
  "api_token": "a00bcd9e-f3gh-20i7-j51k-70l3515mn300"
}
```

The session is valid until it is explicitly deleted (invalidated) or experiences 30 minutes of inactivity.

## Submitting REST API Requests

REST API requests can be performed within a REST session.

The user's [authorization](#) role in Purity determines which requests the client can perform within the session.

Each REST API request is comprised of a complete URL. The complete URL used to make a Pure Storage REST request includes the following components:

- Method (GET, POST, PUT, or DELETE)
- Purity array
- [REST API version](#)
- URI

For example, the following request lists all volumes and their attributes:

```
GET https://pure-001.example.com/api/1.11/volume
```

Some REST API requests include additional parameters.

Parameters for GET methods may be specified as query parameters in the URL. For example, the following request, with space specified as a query parameter, lists array space usage:

```
GET https://pure-001.example.com/api/1.11/array?space=true
```

All other methods (POST, PUT, and DELETE) must be specified as JSON post data. Refer to the <http://www.json.org/> website for more information about the JSON interchange format.

The following are examples of how different data types are formatted in JSON:

| Data Type | Examples                                                           |
|-----------|--------------------------------------------------------------------|
| boolean   | <code>{"eradicate": true}</code>                                   |
| object    | <code>{"replicate_blackout": {"end": 14400, "start": 7200}}</code> |
| list      | <code>{"nameservers": ["192.168.1.1", "192.168.0.1"]}</code>       |
| number    | <code>{"per_day": 12}</code>                                       |
| string    | <code>{"domain": "example.com"}</code>                             |

For example the following request and payload, with the source parameter specified as JSON post data, creates a new volume named v6 by copying volume v1.

```
>> POST https://pure-001.example.com/api/1.11/volume/v6
<< 200 OK
{
  "source": "v1"
}
```

Refer to [Resources](#) for a list of all available Pure Storage REST requests.

Each REST API request returns a [response code](#). Successful requests return the response code 200 OK. Scripts must be prepared to handle responses with codes other than 200 OK.

In the following example, the client is attempting to list alert information for email recipient support\_@purestorage.com. The request returns a response code 400 BAD REQUEST, stating that recipient support\_@purestorage.com does not exist.

```
>> GET http://lt14/api/1.11/alert/support_@purestorage.com
<< 400 BAD REQUEST
{
  msg: "Address does not exist."
  ctx: "support_@purestorage.com"
}
```

Refer to the [Response Codes](#) table for a description of each response code.

Every request that modifies a resource is logged in the Purity [audit trail](#). These requests include most POST, PUT, and DELETE requests. The logged events can be viewed through the Purity GUI (Messages > Audit Trail) and CLI (puremessage list --audit).

## Invalidating a REST Session

A REST session is valid until it is explicitly deleted (invalidated) or experiences 30 minutes of inactivity.

To manually invalidate a REST session, send the following request:

```
>> DELETE https://{array}/api/1.11/auth/session
<< 200 OK
{
  "username": "pureuser"
}
```

## Version Control

The REST API consists of a major and minor version.

Major releases modify or remove existing functionality and are not backward compatible.

Minor releases add new functionality only. Minor releases are backward compatible, with exceptions listed in the REST API release notes. For example, users on REST API version 1.2 can submit any of the requests available in REST API versions 1.0 through 1.2.

To determine the supported REST API versions for the current release, enter the URL `https://{array}/api/api_version`. The supported version numbers are returned as a list. For example,

```
{"version": ["1.0", "1.1", "1.2", "1.3", "1.4", "1.5", "1.6", "1.7", "1.8", "1.9", "1.10", "1.11"]}
```

## Authentication vs. Authorization

The REST API uses authentication tokens instead of credentials to create sessions, while authorization roles determine which requests can be performed within a session.

### Authentication

Purity clients must use an API token in order to securely create REST API sessions. By using API tokens to authenticate, scripts do not have to expose usernames and passwords. The Purity username and password are required initially to create the API token.

API tokens are unique to the Purity user for whom it was created. Each Purity user can generate and view only their own API token. Once created, an API token is valid until it is deleted or recreated.

API tokens can be created and recreated through the Purity GUI (System > Users > Create API Token), CLI (`pureadmin create --api-token`) or REST API.

After obtaining an API token, clients can create REST API sessions and start sending requests. Since REST API service sessions are completely separate from Purity GUI sessions, REST requests cannot be accessed through the Purity GUI.

API token management does not affect Purity usernames and passwords. For example, invalidating an API token does not invalidate the Purity username or password that was used to create the token. Likewise, changing the Purity username or password does not affect the API token.

### Authorization

Authorization determines what the client is permitted to do within a REST session.

If Purity is integrated with a directory service, such as Microsoft Active Directory or OpenLDAP, the REST service leverages role-based access control (RBAC) to determine permission levels. In other words, the roles that are assigned to the users in a directory service are the same roles that are used in Purity and in the REST API.

Once you have created a REST API session, the requests that the client is authorized to make depend on the role of the user associated with the API token (as system administrator, storage administrator, or read-only user).

The integration of RBAC in the REST API with directory services is dynamic. The API token permissions are integrated with the Active Directory permissions. Changes made to a user's Active Directory permissions affect the associated API token permissions.

For example, if a user is moved to a different directory services group and the permission level changes from read-only user to storage administrator, the associated API token permissions change as well. Permission changes made in the directory server are cached on the array and may take 30 minutes to affect the API token.

## Response Codes

The Pure Storage REST API returns the following HTTP response status codes for the GET, POST, PUT, and DELETE operations:

| Code                   | Description                                                                                                                                     |
|------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| 200 OK                 | The request is successful.                                                                                                                      |
| 400 BAD REQUEST        | The request includes an invalid action or invalid or missing data. Refer to the REST API response for more information.                         |
| 401 UNAUTHORIZED       | The REST API session has not been created or has expired. Create a new session.                                                                 |
| 403 FORBIDDEN          | The request is valid, but the client is not authorized to perform the action. For example, a read-only client is not allowed to create volumes. |
| 404 NOT FOUND          | The URI is not valid.                                                                                                                           |
| 405 METHOD NOT ALLOWED | The method is not valid for the URI specified. Enter a GET, POST, PUT, or DELETE method that is valid for the URI specified.                    |

450 VERSION NOT SUPPORTED The request is not valid for the REST API version specified.

500 SERVER ERROR The request generated an internal error. Contact Pure Storage Support for help.

## Sorting, Filtering, and Pagination

When submitting GET requests that return a large amount of data, include filtering, sorting, and pagination query parameters to help you better manage the results.

The Pure Storage REST API supports filtering, sorting, and pagination for the following GET methods: GET volume, GET host, GET hgroup, GET pggroup, and GET port.

### Sorting

The sort query parameter returns the response objects of a GET request in the order specified. Sorting can be performed on any of the fields in the response, and the response objects can be sorted in ascending or descending order.

#### Syntax

?sort=**field\_name**

field\_name

Name of the field to sort. Field\_name can be any of the fields in the response. To sort in descending order, append the minus sign (-) to the field name. To sort on multiple field names, list the field names as comma-separated values.

#### Examples

Example 1: Get a list of all protection groups sorted in ascending order by protection group name.

```
GET https://pure01.example.com/api/1.11/pgroup?sort=name
```

Example 2: Get a list of all host groups sorted in descending order by host group name.

```
GET https://pure01.example.com/api/1.11/hgroup?sort=name-
```

Example 3: Get a list of all volumes sorted in descending order by volume size, and then sorted in ascending order by volume name.

```
GET https://pure01.example.com/api/1.11/volume?sort=size-,name
```

### Filtering

The filter query parameter narrows down the results of a GET request to only the response objects that satisfy the filter criteria.

#### Filtering With Operators

Pure Storage REST API filter queries support common comparison operators.

#### Syntax

?filter=**field\_name operator field\_value**

field\_name

Name of the field on which to create the filter. Field\_name can be any of the fields in the response.

operator

Type of filter match used to compare field\_name to field\_value. Filters support the following operators:

| Operator | Description    | Examples                                                                                                        |
|----------|----------------|-----------------------------------------------------------------------------------------------------------------|
| =        | Equals         | Get a list of all volumes with volume names that include v1.<br><code>/volume?filter=name='*v1*'</code>         |
| !=       | Does not equal | Get a list of all volumes with volume names that do not include v1.<br><code>/volume?filter=name!='*v1*'</code> |
| <        | Less than      | Get a list of all volumes that are less than 100 gigabytes in size.                                             |

|    |                          |                                                                                    |
|----|--------------------------|------------------------------------------------------------------------------------|
| >  | Greater than             | /volume?filter=size<107374182400                                                   |
|    |                          | Get a list of all volumes that are greater than 100 gigabytes in size.             |
|    |                          | /volume?filter=size>107374182400                                                   |
| <= | Less than or equal to    | Get a list of all volumes that were created after 2016-04-25T23:02:23Z.            |
|    |                          | /volume?filter=created>'2016-04-25T23:02:23Z'                                      |
|    |                          | Get a list of all volumes that are less than or equal to 100 gigabytes in size.    |
| >= | Greater than or equal to | /volume?filter=size<=107374182400                                                  |
|    |                          | Get a list of all volumes that were created on or before 2016-04-25T23:02:23Z.     |
|    |                          | /volume?filter=created<='2016-04-25T23:02:23Z'                                     |
| >= | Greater than or equal to | Get a list of all volumes that are greater than or equal to 100 gigabytes in size. |
|    |                          | /volume?filter=size>=107374182400                                                  |
|    |                          |                                                                                    |

#### field\_value

Search value (number, date, or string) that determines the fields to be included in or excluded from the response.

Literal strings must be wrapped in quotes.

To refine the filter, include the asterisk (\*) symbol as a wildcard character in the field value to represent zero or more characters. Field\_value can include multiple asterisks, and the asterisks can appear anywhere in the value. For example, the request GET /host?filter=name='\*cat\*' lists all hosts with names that contain cat, including ones that begin or end with cat, such as cat, catnap, happycats, and lolcat. If the asterisks were not included, only the host named cat would be returned.

#### Examples

Example 1: Get the volume with serial number 31F52075433543110001103F.

```
GET https://pure01.example.com/api/1.11/volume?filter=serial='31F52075433543110001103F'
```

Example 2: Get a list of hosts that are associated with host group ESXi-IT-Cluster02-hg2.

```
GET https://pure01.example.com/api/1.11/host?filter=hgroup='ESXi-IT-Cluster02-hg2'
```

Example 3: Get a list of all Fibre Channel ports on controller ct0.

```
GET https://pure01.example.com/api/1.11/port?filter=name='ct0.fc*'
```

Example 4: Get a list of all volumes that have been destroyed and will be eradicated within the next 2 hours (7200 seconds).

```
GET https://pure01.example.com/api/1.11/volume?pending_only=true&filter=time_remaining<='7200'
```

#### Filtering With Functions

Pure Storage REST API filter queries support the CONTAINS and NOT functions.

#### Syntax

?filter=function(parameters)

Filters support the following functions:

| Function                     | Description                                                                                                                                                                                                       | Examples                                                                                                           |
|------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------|
| contains(field_name, string) | Contains the enclosed string.<br><br>Takes exactly two parameters, where field_name represents the name of the field on which to create the filter, and string represents the string to search within field_name. | Get a list of all host groups with names that include cluster02.<br><br>/host?filter=contains(hgroup, 'cluster02') |
| not(expression)              | Inverse of the enclosed expression.                                                                                                                                                                               | Get a list of all host groups with names that do not                                                               |

include cluster02.

/host?filter=not(hgroup='cluster02')

**Examples**

Example 1: Get a list of all hosts that are associated with host groups that include hg3 in the host group name.

```
GET https://pure01.example.com/api/1.11/host?filter=contains(hgroup, 'hg3')
```

Example 2: Get a list of all volumes with names that do not include vol01.

```
GET https://pure01.example.com/api/1.11/volume?filter=not(contains(name, 'vol01'))
```

**Existence Checks**

The REST API supports existence checks. For example, the request GET /volume?filter=name checks to see if "name" field name exists in the volume resource.

**Examples**

Example 1: Get a list of all hosts that are associated with a host group.

```
GET https://pure01.example.com/api/1.11/host?filter=hgroup
```

Example 2: Get a list of all volumes that were not created from another source.

```
GET https://pure01.example.com/api/1.11/volume?filter=not(source)
```

Example 3: Get a list of all hosts that are not associated with Fibre Channel WWNs. (Sample response included.)

```
>> GET https://pure01.example.com/api/1.11/host?filter=not(wwn)
<< {
  "iqn": [],
  "wwn": [],
  "name": "ESXi-Cluster02-v7",
  "hgroup": null
},
{
  "iqn": [],
  "wwn": [],
  "name": "ESXi-Cluster02-v8",
  "hgroup": "ESXHGroup1"
},
{
  "iqn": [],
  "wwn": [],
  "name": "ESXi-Cluster02-v9",
  "hgroup": null
},
{
  "iqn": [],
  "wwn": [],
  "name": "ESXi-Cluster02-v10",
  "hgroup": null
}
```

Example 4: Get a list of all protection groups that do not contain volume or host group members.

```
GET https://pure01.example.com/api/1.11/pgroup?filter=not(volumes) and not(hgroups)
```

**Pagination**

Pagination controls the amount of data returned by displaying response objects (items) as page-by-page lists.

Pagination only applies if the total number of items returned is greater than the limit specified. To determine the total number of items returned, see the x-total-item-count header field of the response.

The Pure Storage REST API offers two methods of pagination: page by index, and page by continuation token.

**Page by Index**

Page by index enables clients to control the size and starting point of a page. Use page by index, such as in GUI implementations, to navigate through response objects page by page, jump to specific pages, and jump to the first or last page. For example, to page through all results with 20 results per page, begin with `start=0&limit=20`.

With page by index pagination, consistency may not be guaranteed in that some data may be duplicated or missing across pages. If consistency is important, use continuation tokens.

### Syntax

`start=starting_index&limit=items_returned`

`starting_index`

Index number of the first item you want results for.

`items_returned`

Maximum number of response objects returned per page.

### Examples

Example 1: Get all volumes starting at the very first volume.

```
GET https://pure01.example.com/api/1.11/volume?start=0
```

Example 2: Get 10 volumes at a time.

```
GET https://pure01.example.com/api/1.11/volume?limit=10
```

Example 3: Get 10 volumes with index 0 to 9.

```
GET https://pure01.example.com/api/1.11/volume?start=0&limit=10
```

Example 4: Get 1 host with index 100.

```
GET https://pure01.example.com/api/1.11/hosts?start=100&limit=1
```

### Page by Continuation Token

The REST API supports continuation tokens, giving clients the ability to paginate with some consistency guaranteed.

Page by continuation token requires the `limit` and `token` query parameters.

The `limit` parameter determines how many response objects (items) are returned on each page.

The `token` parameter is a Base64 encoded value that is used to get the next page of data. The token is taken from the `x-next-token` header field of the response. A query has reached its last page when the response does not include a token.

### Syntax

`limit=items_returned&token=token`

`items_returned`

Maximum number of response objects returned per page.

`token`

Token of the last/first item returned in the current paginated request. The token is used in the next submit to determine the first item that should appear on the next page. The token appears in the response header. To ensure consistent paging, the `token` parameter must always be used with the `sort` parameter.

### Examples

Example 1: Use token `awQgPSA50DA1Mg==` to get the next 10 volumes.

```
GET https://pure01.example.com/api/1.11/volume?limit=10&token=awQgPSA50DA1Mg==
```

Example 2: Use token `c3JjX2FwdCA9IDY2LG1kID0gMQ==` to get the next 10 protection groups.

```
GET https://pure01.example.com/api/1.11/pgroup?limit=10&token=c3JjX2FwdCA9IDY2LG1kID0gMQ==
```

Example 3: Get 2 volumes with index 5 to 9, and then use the token returned (awQgPSA20TY1NA==) to get the next 2 volumes.

```
>> GET https://pure01.example.com/api/1.11/volume?start=5&limit=2

<< x-next-token → aWQgPSA20TY1NA==
x-total-item-count → 21

<< {
  "source": null,
  "serial": "122E64ABC3FE4BA100011015",
  "created": "2016-04-28T20:30:56Z",
  "name": "ESXi-Cluster02-vol005",
  "size": 107374182400
},
{
  "source": null,
  "serial": "122E64ABC3FE4BA100011016",
  "created": "2016-04-28T20:30:56Z",
  "name": "ESXi-Cluster02-vol007",
  "size": 107374182400
}

>> GET https://pure01.example.com/api/1.11/volume?limit=2&token=aWQgPSA20TY1NA==

<< x-next-token → aWQgPSA20TY2MQ==
<< {
  "source": null,
  "serial": "122E64ABC3FE4BA10001101C",
  "created": "2016-04-28T20:30:56Z",
  "name": "ESXi-Cluster02-vol006",
  "size": 107374182400
},
{
  "source": null,
  "serial": "122E64ABC3FE4BA10001101D",
  "created": "2016-04-28T20:30:56Z",
  "name": "ESXi-Cluster01-vol001",
  "size": 107374182400
}
```

Example 4: Get one protection group at a time using the token returned each time to get the next protection group.

```
>> GET https://pure01.example.com/api/1.11/pgroup?limit=1

<< x-next-token → c3JjX2FwdCA9IDY2LGlkID0gMQ==
x-total-item-count → 10
<< {
  "name": "PG001",
  "hgroups": null,
  "source": "pure001",
  "hosts": [
    "ESXi-PROD-Cluster01-h2",
    "ESXi-STG-Cluster03-h2"
  ],
  "volumes": null,
  "targets": null
}

>> GET https://pure01.example.com/api/1.11/pgroup?limit=1&token=c3JjX2FwdCA9IDY2LGlkID0gMQ==

<< x-next-token → c3JjX2FwdCA9IDY2LGlkID0gMg==
<< {
  "name": "PG002",
  "hgroups": null,
  "source": "pure001",
  "hosts": [
    "ESXi-GRP-Cluster02-h2",
    "ESXi-GRP-Cluster02-h3"
  ],
  "volumes": null,
  "targets": null
}

>> GET https://pure01.example.com/api/1.11/volume?limit=1&token=c3JjX2FwdCA9IDY2LGlkID0gMg==

<< x-next-token → c3JjX2FwdCA9IDY2LGlkID0gMw==
<< {
  "name": "PG003",
  "hgroups": null,
  "source": "pure005",
  "hosts": null,
  "volumes": [
    "ESXi-Cluster01-vol007",
    "ESXi-Cluster01-vol010",
    "ESXi-Cluster01-vol009",
    "ESXi-Cluster01-vol008"
  ],
  "targets": null
}
```

## Combining Sorting, Filtering, and Pagination

Follow these guidelines when combining sorting, filtering, and pagination:

- Sort queries can be combined. A single request can be sorted on multiple field names. For example, you can sort all volumes from largest to smallest volume size, and then sort volumes of the same size in ascending order by volume name. To sort on multiple field names, list the field names as comma-separated values.
- Filter queries can be combined using the AND and OR operators. The AND operator displays response objects that meet the criteria of all filter queries in the request. The OR operator displays response objects that meet the criteria of at least one of the filter queries in the request.
- The sort, filter, limit, and start filters can all be combined together.

### Examples

Example 1: Get a list of all volumes sorted in descending order by volume size, and then sorted in ascending order by volume name.

```
GET https://pure01.example.com/api/1.11/volume?sort=size-,name
```

Example 2: Get a list of all hosts with names that include h2 and are associated with host groups with names that include hg3.

```
GET https://pure01.example.com/api/1.11/host?filter=(contains(name,'h2') and contains(hgroup,'hg3'))
```

Example 3: Get a list of all volumes that are greater than 10 gigabytes in size and were created after 2016-04-25T23:02:23Z.

```
GET https://pure01.example.com/api/1.11/volume?filter=size>10737418240 and created>'2016-04-25T23:02:23Z'
```

Example 4: Get a list of all volumes that begin with v1, and sort the list in descending order by name.

```
GET https://pure01.example.com/api/1.11/volume?filter=name='v1*&sort=name-
```

Example 5: Get a list of either all volumes with names that include 123 and are greater than or equal to 10 gigabytes in size, or all volumes with names that include abc and are less than or equal to 10 gigabytes in size.

```
GET https://pure01.example.com/api/1.11/volume?filter=(contains(name,'123') and size >= 10737418240)
or (contains(name,'abc') and size <= 10737418240)
```

## Audit Trail

Every request that creates, modifies, or deletes a resource will be logged in the audit trail, which can be viewed through the Purity GUI (Messages > Audit Trail) and CLI (puremessage). For example, if the client sends the following request to create a snapshot of volume v1, the action, including the username of the user associated with the API token, is logged in the audit trail:

```
>> POST https://pure-001.example.com/api/1.11/volume
<< 200 OK
{
  "snap": true,
  "source": [
    "v1"
  ]
}
```

## REST API and Scripting

### Session Management

The client that makes the REST API requests will need to store a cookie returned by the REST service in order to continue to use the session. When using Python to create REST scripts, the CookieJar library can be used to manipulate session cookies. For example,

```
cj = CookieJar()
opener = urllib2.build_opener(urllib2.HTTPCookieProcessor(cj))
urllib2.install_opener(opener)
```

Refer to the `cookielib` module at [docs.python.org](https://docs.python.org) for more information about cookie handling. Refer to RFC 2109 for protocol standards and recommendations about setting cookies.

## Content Type

The request header must be set to the “application/json” content type. When using Python to create REST scripts, set the content-type header value to application/json. For example,

```
headers = {"Content-Type": "application/json"}
req = urllib2.Request(url, headers=headers)
```

[Back to top](#)

## Release Notes

This section outlines the changes made to the REST API.

### Compatibility Changes

The following compatibility changes affect all versions of the REST API and potentially break pre-existing API requests.

| Description                                                                      | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | Purity Versions  |
|----------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------|
| Changed the output of the <b>GET drive</b> and <b>GET drive/{drive}</b> requests | <p>The output of the <b>GET drive</b> and <b>GET drive/{drive}</b> requests is changed when the value of the type field is null. The output previously returned "-" in the type field for a null value. Now null is returned in the type field for a null value.</p> <p>This change affects all versions of the REST API, when connecting with FlashArrays running Purity 4.10.0 or later versions.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        | 4.10.0 and later |
| Made <b>GET message</b> open and audit options incompatible                      | <p>The open and audit parameters are not supported together in the same <b>GET message</b> REST API request.</p> <p>This change affects all versions of the REST API, when connecting with FlashArrays running Purity 4.5.0 or later versions.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             | 4.5.0 and later  |
| Deprecated DRV component name                                                    | <p>The DRV component name is deprecated. This change affects the following requests:</p> <ul style="list-style-type: none"> <li>Deprecated DRV information in the response of <b>GET hardware</b> requests. Information for the BAY component name is still reported.</li> <li>Deprecated DRV in the <b>GET hardware/{component}</b> request URL. Instead, use the BAY component name with a <b>GET drive/{component}</b> request.</li> </ul> <p>For example, deprecated GET <code>https://pure01.example.com/api/1.4/hardware/SH0.DRV0</code>.<br/>Instead, use GET <code>https://pure01.example.com/api/1.4/drive/SH0.BAY0</code>.</p> <p>(Note: The BAY component name is still available with the <b>GET hardware/{component}</b> request, but the <b>GET drive/{component}</b> request above is preferred.)</p> <p>The DRV deprecation affects all versions of the REST API, when connecting with FlashArrays running Purity 4.1.4 or later versions.</p> | 4.1.4 and later  |
| Removed method stub <b>PUR port</b>                                              | <p>Removed the method stub <b>PUR port</b>, which was inadvertently exposed.</p> <p>This removal affects all versions of the REST API, when connecting with FlashArrays running Purity 4.1.0 or later versions.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | 4.1.0 and later  |

## TLS Requirements

With the release of Purity 4.7.0, support for TLS 1.0 is dropped for all versions of the REST API.

The following table lists the TLS versions required to communicate with the Pure Storage REST API:

| Purity Version | Supported TLS Versions |
|----------------|------------------------|
|----------------|------------------------|

|                            |                       |
|----------------------------|-----------------------|
| Purity 4.7.0 and later     | TLS 1.1 and 1.2       |
| Earlier versions of Purity | TLS 1.0, 1.1, and 1.2 |

## REST API 1.11

This section describes changes made between REST API 1.10 and REST API 1.11.

| Description                                                                             | Details                                                                                                                                                                                                                                                                                                |
|-----------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added new field to the output of <b>GET drive</b> and <b>GET drive/{drive}</b> requests | <p>Added the protocol field to the output of <b>GET drive</b> and <b>GET drive/{drive}</b> requests. The protocol field currently returns these values:</p> <ul style="list-style-type: none"> <li>• SAS: for drives with SAS connections</li> <li>• NVMe: for drives with NVMe connections</li> </ul> |

## REST API 1.10

This section describes changes made between REST API 1.9 and REST API 1.10.

| Description                   | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|-------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added SAN latency information | <p>Changed the response of the <b>GET array?action=monitor</b>, <b>GET hgroup?action=monitor</b>, <b>GET host?action=monitor</b>, and <b>GET volume?action=monitor</b> requests. The following fields no longer include SAN latency:</p> <ul style="list-style-type: none"> <li>• usec_per_read_op: displays the average arrival-to-completion time for a host read operation (microseconds)</li> <li>• usec_per_write_op: displays the average arrival-to-completion time for a host write operation (microseconds)</li> </ul> <p>Added the following fields to report SAN latency:</p> <ul style="list-style-type: none"> <li>• san_usec_per_read_op: displays the average time required to transfer data from the array to the initiator (microseconds)</li> <li>• san_usec_per_write_op: displays the average time required to transfer data from the initiator to the array (microseconds)</li> </ul> |

## REST API 1.9

This section describes changes made between REST API 1.8 and REST API 1.9.

| Description                 | Details                                                                                                                                                                                                                                                                                                 |
|-----------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added support for Pure Apps | <p>Added following endpoints to display information about installed apps:</p> <ul style="list-style-type: none"> <li>• <b>GET app</b> to display information about all installed apps</li> <li>• <b>GET app/{app}</b> to display information about a specific app</li> </ul>                            |
| Added support for IPv6      | <p>On arrays running Purity 4.9.0 and above, IPv6 addresses can be passed anywhere an IPv4 address could be passed using any REST version.</p> <p><b>Note:</b> In a mixed environment with some arrays running Purity 4.8.x or below, using REST API 1.9 guarantees that the request supports IPv6.</p> |

## REST API 1.8

This section describes changes made between REST API 1.7 and REST API 1.8.

### Compatibility Changes in REST API 1.8

| Description                                                     | Details                                                                                                                                                                                                                                                                                        |
|-----------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Changed the response returned by the <b>GET drive</b> requests. | <p>Removed the degraded field from the responses of the <b>GET drive</b> and <b>GET drive/{drive}</b> requests. Previously, the degraded field displayed the percentage of data that is not protected by redundancy.</p> <p><b>Note:</b> This change affects all versions of the REST API.</p> |

The `parity` field in the response of **GET array?space=true** request now provides data redundancy information that previously appeared in the `degraded` field.

**Note:** The `parity` field is only available in version 1.8 and higher of the REST API.

## Other REST API 1.8 Changes

| Description                                                              | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|--------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added information about data redundancy to the <b>GET array</b> response | <p>Added the <code>parity</code> field, showing the percentage of data that is protected by RAID-6, to the response returned by the <b>GET array?space=true</b> request.</p> <p>The percentage value drops below 100% if the data is not fully protected, such as when a module is pulled and the array is rebuilding the data to bring it back to full parity.</p> <p><b>Note:</b> The <code>parity</code> field returns null when the <code>historical</code> parameter is used.</p> |
| Added voltage information to <b>GET hardware</b> responses               | Added the <code>voltage</code> field to the responses of the <b>GET hardware</b> and <b>GET hardware/{component}</b> requests.                                                                                                                                                                                                                                                                                                                                                         |

## REST API 1.7

This section describes changes made between REST API 1.6 and REST API 1.7.

### Compatibility Changes in REST API 1.7

| Description                                                         | Details                                                                                                                                                                                                                                                                                                                                    |
|---------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Changed the response returned by protection group snapshot transfer | <p>Removed the <code>queued</code> field from the response of the <b>GET pggroup/{pggroup}?snap=true&amp;transfer=true</b> request.</p> <p>The <code>started</code> field now provides the data that previously appeared in the <code>queued</code> field.</p> <p><b>Note:</b> This change also affects REST API 1.5 and REST API 1.6.</p> |
| Changed the response returned by phonehome                          | In 4.7.x release and 4.6.x releases after 4.6.4, the response to the <b>GET array/phonehome</b> request was: <code>{"status": "", "action": ""}</code> . In 4.8.0, the response is changed back to <code>{"status": null, "action": null}</code> to be backwards compatible with 4.1.x and 4.5.x releases.                                 |

## Other REST API 1.7 Changes

| Description                                                                                | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|--------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added the ability to add and remove hosts, host groups, and volumes from protection groups | <p>Added the following endpoints to add or remove hosts, host groups, and volumes to and from protection groups:</p> <ul style="list-style-type: none"> <li>• <b>POST host/{host}/pgroup/{pgroup}</b> to add a host to a protection group</li> <li>• <b>POST hgroup/{hgroup}/pgroup/{pgroup}</b> to add a host group to a protection group</li> <li>• <b>POST volume/{volume}/pgroup/{pgroup}</b> to add a volume to a protection group</li> <li>• <b>DELETE host/{host}/pgroup/{pgroup}</b> to remove a host from a protection group</li> <li>• <b>DELETE hgroup/{hgroup}/pgroup/{pgroup}</b> to remove a host group from a protection group</li> <li>• <b>DELETE volume/{volume}/pgroup/{pgroup}</b> to remove a volume from a protection group</li> </ul>                                                                                                                                                                                                                                                            |
| Added the ability to list protection group membership for hosts, host groups, and volumes  | <p>Added the <code>protect</code> parameter to the following endpoints:</p> <ul style="list-style-type: none"> <li>• <b>GET host?protect=true</b> to display all protected hosts and their associated protection groups</li> <li>• <b>GET hgroup?protect=true</b> to display all protected host groups and their associated protection groups</li> <li>• <b>GET volume?protect=true</b> to display all protected volumes and their associated protection groups</li> <li>• <b>GET host/{host}?protect=true</b> to display protection group membership for a specific host</li> <li>• <b>GET hgroup/{hgroup}?protect=true</b> to display protection group membership for a specific host group</li> <li>• <b>GET volume/{volume}?protect=true</b> to display protection group membership for a specific volume</li> </ul> <p>Set the <code>protect</code> value to <code>true</code> to list protection group membership for hosts, host groups, and volumes.</p> <p>The <code>protect</code> parameter is optional.</p> |
| Added support for filtering, limiting, pagination, and sorting                             | <p>Filtering narrows down the results of a GET request.</p> <p>Limiting restricts the number of entries returned in the results of a GET request.</p> <p>Pagination displays the results of a GET request as page-by-page lists.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |

Sorting returns the response objects of a GET request in the order specified.

See the [Sorting, Filtering, and Pagination](#) section.

|                                                                                                             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|-------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added port failover status                                                                                  | The <b>GET port</b> endpoint now also returns the failover status of ports (NPIV status of FC ports).                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| Added ability to display private and shared connections and to display LUNs used in host-volume connections | <p>Added the <code>connect</code> parameter to the following endpoints:</p> <ul style="list-style-type: none"> <li>• <b>GET hgroup</b></li> <li>• <b>GET host</b></li> <li>• <b>GET volume</b></li> </ul> <p>Set the <code>connect</code> value to <code>true</code> to display private or shared host-volume connections and the LUNs used by the hosts to address the volumes.</p> <p>The <code>connect</code> parameter is optional.</p> <p>Added the <code>private</code> and <code>shared</code> parameters to the following endpoints:</p> <ul style="list-style-type: none"> <li>• <b>GET host</b></li> <li>• <b>GET volume</b></li> </ul> <p>Set the <code>private</code> value to <code>true</code> to display private host-volume connections and the LUNs used by the hosts to address the volumes.</p> <p>Set the <code>shared</code> value to <code>true</code> to display shared host-volume connections and the LUNs used by the hosts to address the volumes.</p> <p>The <code>private</code> and <code>shared</code> parameters are optional and are only valid if the <code>connect</code> parameter is set to <code>true</code>.</p> |
| Added ability to query specific object names (for hosts, host groups, protection groups, and volumes)       | <p>Added the <code>names</code> parameter to the following endpoints to restrict the returned output to only the named objects:</p> <ul style="list-style-type: none"> <li>• <b>GET hgroup</b></li> <li>• <b>GET host</b></li> <li>• <b>GET pgroup</b></li> <li>• <b>GET volume</b></li> </ul> <p>The <code>names</code> parameter accepts a single name or a comma-separated list for multiple values. The <code>names</code> parameter also accepts an asterisk (*) as a wildcard character.</p> <p>The <code>names</code> parameter is optional, as is the asterisk wildcard character.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| Added limited support for asterisk as a wildcard character                                                  | <p>An asterisk (*) wildcard character representing zero or more unspecified characters is supported in filters and in the <code>names</code> parameter when used with the following objects:</p> <ul style="list-style-type: none"> <li>• Hosts</li> <li>• Host groups</li> <li>• Protection groups</li> <li>• Protection group snapshots</li> <li>• Volumes</li> </ul> <p>The asterisk wildcard character is optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Added size and total options to monitor resources                                                           | <p>Added <code>size</code> parameter to the following endpoints:</p> <ul style="list-style-type: none"> <li>• <b>GET array</b></li> <li>• <b>GET host</b></li> <li>• <b>GET host/{host}</b></li> <li>• <b>GET hgroup</b></li> <li>• <b>GET hgroup/{hgroup}</b></li> <li>• <b>GET volume</b></li> <li>• <b>GET volume/{volume}</b></li> </ul> <p>Set the <code>size</code> value to <code>true</code> to display the average I/O sizes.</p> <p>The <code>size</code> parameter is optional and is only valid if the <code>action</code> parameter is set to <code>monitor</code>.</p> <p>Added the <code>total</code> parameter to the following endpoints:</p> <ul style="list-style-type: none"> <li>• <b>GET hgroup</b></li> <li>• <b>GET host</b></li> <li>• <b>GET volume</b></li> </ul> <p>Set the <code>total</code> value to <code>true</code> to append a row containing aggregated data.</p> <p>The <code>total</code> parameter is optional and is only valid if the <code>action</code> parameter is set to <code>monitor</code>.</p>                                                                                                        |

## REST API 1.6

The following changes were made between REST API 1.5 and REST API 1.6:

| Description                                                            | Details                                                                                                                                                                                                                                                        |
|------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to list historical storage capacity and utilization data | For the <b>GET array</b> , <b>GET volume</b> , and <b>GET volume/{volume}</b> requests, added the ability to use the <code>historical</code> parameter with the <code>space=true</code> parameter to display historical storage capacity and utilization data. |

**Note:** See also [REST 1.7 Compatibility Changes](#) for a change to the response returned by a protection group snapshot transfer request. This change is also made in REST 1.5 and REST 1.6.

## REST API 1.5

The following changes were made between REST API 1.4 and REST API 1.5:

| Description                                                                                    | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to list performance data for hosts, host groups, volumes, or snapshots           | <p>Added the <code>action=monitor</code> value to the following requests to display real-time I/O performance data:</p> <ul style="list-style-type: none"> <li>• <b>GET host</b> to display data for all hosts</li> <li>• <b>GET host/{host}</b> to display data for the specified host</li> <li>• <b>GET hgroup</b> to display data for all hosts</li> <li>• <b>GET hgroup/{hgroup}</b> to display data for the specified host</li> </ul> <p>Added the <code>action=monitor</code> value to the <b>GET volume</b> request to display real-time or historical performance data. Combine with the <code>historical</code> parameter to display historical data.</p> <p>The <code>action</code> parameter is optional.</p> |
| Added ability to specify multiple protection groups with the <code>pgrouplist</code> parameter | The <b>GET volume</b> and <b>GET volume/{volume}</b> requests now accept either a single protection group or a comma-separated list of protection groups in the <code>pgrouplist</code> parameter. When multiple protection groups are specified, the request returns information for all snapshots that were created for any of the specified protection groups. Previously, the <code>pgrouplist</code> parameter accepted only a single protection group.                                                                                                                                                                                                                                                             |
| Added ability to specify optional Boolean parameters as <code>false</code>                     | <p>This code change does not modify API request behavior, except to allow an optional Boolean parameter to be set to <code>false</code>. Setting an optional Boolean parameter to <code>false</code> is equivalent to not including the parameter in the request.</p> <p>Previously, optional Boolean parameters only accepted <code>true</code>. The following are examples of optional Boolean parameters that now also accept <code>false</code>:</p> <ul style="list-style-type: none"> <li>• <code>GET admin?api_token</code></li> <li>• <code>GET admin?expose</code></li> <li>• <code>GET admin?publickey</code></li> <li>• <code>GET array?controllers</code></li> <li>• <code>GET host?all</code></li> </ul>    |
| Added ability to copy protection groups                                                        | <p>Added the <code>source</code> and <code>overwrite</code> parameters to the <b>POST pgroupl/{pgroupl}</b> request to enable the copying of protection groups.</p> <p>The <code>source</code> and <code>overwrite</code> parameters are optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| Added ability to manage subnets and virtual network interfaces                                 | <p>Added the following resources to support VLAN tagging:</p> <ul style="list-style-type: none"> <li>• <b>GET subnet</b> and <b>GET subnet/{subnet}</b> to list subnets</li> <li>• <b>POST subnet/{subnet}</b> to create a subnet</li> <li>• <b>PUT subnet/{subnet}</b> to set subnet attributes</li> <li>• <b>DELETE subnet/{subnet}</b> to delete a subnet</li> <li>• <b>POST network/vif</b> to create a VLAN interface</li> <li>• <b>DELETE network/vif</b> to delete a VLAN interface</li> </ul>                                                                                                                                                                                                                    |
| Added ability to manage traffic between connected arrays                                       | Added the <b>PUT array/connection/{connection}</b> resource to modify bandwidth throttling attributes for a connected array.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Added controller name to <b>GET array/remotassist</b> response                                 | Changed <b>GET array/remotassist</b> to include the controller's hostname in the request response.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |

Removed ability to expose the API tokens of other users

Changed the **GET admin** expose parameter to unmask only the API token of the current user when set to `true`. Previously, setting the expose parameter to `true` unmasked the API tokens of all users.

**Note:** See also [REST 1.7 Compatibility Changes](#) for a change to the response returned by a protection group snapshot transfer request. This change is also made in REST 1.5 and REST 1.6.

## REST API 1.4

The following changes were made between REST API 1.3 and REST API 1.4:

| Description                                                                                                                                                            | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to list user login sessions                                                                                                                              | <p>Added the <b>GET message</b> login parameter to list user session logs.</p> <p>Include the recent parameter with login to display login, logout, and authentication events that have occurred within the past 24 hours.</p> <p>Include the user parameter with login to list user session logs for a specific user.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Added ability to list volume snapshots created as part of one or more protection groups or protection group snapshots                                                  | <p>When the <b>GET volume</b> pgrouplist parameter is set, the REST API lists all volume snapshots that were created as part of protection group snapshots for the specified protection group or protection group snapshot.</p> <p>When the <b>GET volume{volume}</b> pgrouplist parameter is set, the REST API lists the volume snapshots of the specified volume that were created as part of protection group snapshots for the specified protection group.</p> <p>The pgrouplist parameter is optional and is only valid if snap is true.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| Added ability to recover and rename volume snapshots                                                                                                                   | <p>Added the ability to recover and rename volume snapshots through <b>PUT volume{volume}</b>.</p> <p>Previously, <b>PUT volume{volume}</b> resized, recovered and renamed volume names only.</p> <p>Now, <b>PUT volume{volume}</b> can also recover and rename volume snapshots. When renaming a volume snapshot, only the suffix can be changed.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Added ability to generate a snapshot for multiple protection groups specified                                                                                          | <p>Added the ability to generate a snapshot for multiple protection groups specified through the <b>POST pgroup</b> source parameter.</p> <p>Previously, the source parameter only accepted one protection group. Now, the source parameter accepts a list of protection groups.</p> <p>The source parameter is required and is only valid if snap is true.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| Added ability to specify whether snapshot data should be immediately replicated, or queued up to begin replicating after all earlier replication sessions are complete | <p>Added the ability to specify whether snapshot data should be:</p> <ul style="list-style-type: none"> <li>Immediately replicated (<b>POST pgroup</b> replicate_now) to each allowed target, or</li> <li>Queued up (<b>POST pgroup</b> replicate) and only begin replicating to each allowed target after all earlier replication sessions for the same protection group have been completed to that target.</li> </ul> <p>When the <b>POST pgroup</b> replicate_now parameter is set, the REST API immediately replicates the snapshot data to all allowed target arrays.</p> <p>When the <b>POST pgroup</b> replicate parameter is set, the REST API queues the snapshot for replication to all allowed target arrays, excluding sessions started with replicate_now. Purity will begin replicating data to each allowed target when all earlier replication sessions for the same protection group have been completed to that target.</p> <p>The replicate_now and replicate parameters are optional and cannot be used together.</p> |
| Added ability to specify a preferred time of day at which to generate local snapshots                                                                                  | <p>Added the ability to specify the preferred time, on the hour, at which to generate local snapshots through the <b>PUT pgroupl{pgroup}</b> snap_at parameter.</p> <p>The snap_at parameter is optional and is only valid if snap_frequency is set to 3600 or more seconds.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| Changed <b>POST snmp{manager}</b> host parameter to be a required parameter                                                                                            | <p>Changed the <b>POST snmp{manager}</b> host parameter from an optional to required parameter.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| Deprecated ability to list all volume snapshots that have been created as part of protection group snapshots                                                           | <p>Deprecated the ability to list all volume snapshots that have been created as part of protection group snapshots through the <b>GET volume</b> pgroupl and <b>GET volume{volume}</b> pgroupl parameters.</p> <p>A new parameter named pgrouplist has been created to perform similar requests.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |

## REST API 1.3

The following changes were made between REST API 1.2 and REST API 1.3:

| Description                                          | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to view and manage SSL certificates    | <p>Added the following resources to view and manage SSL certificates:</p> <ul style="list-style-type: none"> <li>• <b>GET cert</b> to list certificate attributes or export certificates.</li> <li>• <b>GET cert/certificate_signing_request</b> to construct a certificate signing request (CSR) for signing by a certificate authority (CA).</li> <li>• <b>PUT cert</b> to create a self-signed certificate or import a certificate signed by a certificate authority (CA).</li> </ul> |
| Added ability to clear the replicate_at time         | Added the ability to clear the <b>PUT pgroup/{pgroup}</b> replicate_at parameter by passing in a null value.                                                                                                                                                                                                                                                                                                                                                                             |
| Added ability to clear the replicate_blackout period | Added the ability to clear the <b>PUT pgroup/{pgroup}</b> replicate_blackout parameter by passing in a null value.                                                                                                                                                                                                                                                                                                                                                                       |
| Changed the response of the replicate_blackout field | <p>If the <b>PUT pgroup/{pgroup}</b> replicate_blackout parameter is set to a null value, the replicate_blackout field for <b>GET pgroup/{pgroup}</b> returns an empty response.</p> <p>Before, replicate_blackout returned the response [{"start": 0, "end": 0}].</p>                                                                                                                                                                                                                   |

## REST API 1.2

The following changes were made between REST API 1.1 and REST API 1.2:

| Description                                                      | Details                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to connect and disconnect arrays                   | <p>Added the following resources to manage array connections:</p> <ul style="list-style-type: none"> <li>• <b>GET array/connection</b> to list the connected arrays.</li> <li>• <b>GET array?connection_key=true</b> to list the connection key.</li> <li>• <b>POST array/connection</b> to connect an array.</li> <li>• <b>DELETE array/connection/{connection}</b> to disconnect an array.</li> </ul>                                                                                                                                                                                                    |
| Added ability to manage protection groups                        | <p>Added the following resources to manage protection groups:</p> <ul style="list-style-type: none"> <li>• <b>GET pgroup</b> to list protection groups and their attributes.</li> <li>• <b>GET pgroup/{pgroup}</b> to list the attributes for the specified protection group.</li> <li>• <b>POST pgroup{pgroup}</b> to create a protection group with the specified name.</li> <li>• <b>PUT pgroup{pgroup}</b> to modify a protection group, its retention schedule, and its snapshot schedule.</li> <li>• <b>DELETE pgroup{pgroup}</b> to destroy a protection group and all of its snapshots.</li> </ul> |
| Deprecated ability to rename volume snapshots                    | <p>Deprecated the ability to rename snapshots through the <b>PUT volume/{volume}</b> name parameter.</p> <p>If the Purity client attempts to rename snapshots, the REST API returns response error code 400 BAD REQUEST.</p> <p>This change also impacts REST API versions 1.0 and 1.1.</p>                                                                                                                                                                                                                                                                                                                |
| Added various fields to the <b>POST volume/{volume}</b> response | Added the following fields to the <b>POST volume/{volume}</b> response: source, serial, size and created.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

## REST API 1.1

The following changes were made between REST API 1.0 and REST API 1.1:

| Description                                   | Details                                                                                                                                                                                                       |
|-----------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Added ability to overwrite an existing volume | <p>Added the overwrite parameter to <b>POST volume/{volume}</b>. When used with source, set the overwrite value to true to overwrite an existing volume.</p> <p>Boolean (true or false).</p> <p>Optional.</p> |
| Renamed parameter from force                  | Renamed the <b>PUT directoryservice</b> parameter from force to trust. When used with certificate, set the trust value                                                                                        |

|                                  |                                                                                                                                                    |
|----------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| to trust                         | to true to skip certificate chain trust verification.<br><br>Boolean (true or false).<br><br>Optional.                                             |
| Fixed a bug in <b>GET volume</b> | In v1.0, calls to <b>GET volume</b> with space set to true failed to return values for thin_provisioning and total_reduction. This has been fixed. |

[Back to top](#)

## Resources

[Authentication](#)[Array](#)[Volumes and Snapshots](#)[Hosts](#)[Host Groups](#)[Protection Groups](#)[Connection Ports](#)[Alerts and Messages](#)[SNMP Manager Connections](#)[SSL Certificate](#)[Network Interface](#)[Hardware Components](#)[Apps](#)[Users](#)

### 1. Authentication

Create and destroy REST sessions.

#### 1.1 POST auth/apitoken

Generates a REST API token that can be used to create a REST session.

API tokens are tied to a particular administrative account. Each administrator has permission to manage their own API token. Administrators cannot manage tokens on behalf of other users.

##### Parameters

| Parameter | Type   | Description                                                                                                           |
|-----------|--------|-----------------------------------------------------------------------------------------------------------------------|
| password  | string | Purity user login password used to generate the REST API token.<br><br>Required.                                      |
| username  | string | Purity user login name used to generate the REST API token. Sometimes referred to as sAMAccountName.<br><br>Required. |

##### Example 1: Create an API token

Request:

```
POST https://pure01.example.com/api/1.11/auth/apitoken
{
  "password": "pureuser",
  "username": "pureuser"
```

```
}

```

Response:

```
{
  "api_token": "979bca19-4531-2c39-9230-9c17c47554cb"
}
```

## 1.2 POST auth/session

Creates a REST session using the REST API token.

### Parameters

| Parameter | Type   | Description                                                |
|-----------|--------|------------------------------------------------------------|
| api_token | string | REST API token used to create a REST session.<br>Required. |

### Example 1: Create a REST session

Request:

```
POST https://pure01.example.com/api/1.11/auth/session
{
  "api_token": "$APITOKEN"
}
```

Response:

```
{
  "username": "os76"
}
```

## 1.3 DELETE auth/session

Deletes (invalidates) the REST session.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Delete (invalidate) a REST session

Request:

```
DELETE https://pure01.example.com/api/1.11/auth/session
```

Response:

```
{
  "username": "os76"
}
```

## 2. Array

View and manage the array, and administer the phonehome and remote assist features.

## 2.1 GET array

Lists the attributes for the array, including the array name, Purity version and Purity revision number. Can also display historical performance or capacity data.

### Parameters

| Parameter      | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|----------------|---------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action         | string  | <p>If set to monitor, displays the following real-time or historical performance data:</p> <p><b>Latency</b></p> <ul style="list-style-type: none"> <li>san_usec_per_read_op - average time, measured in microseconds, required to transfer data from the array to the initiator.</li> <li>san_usec_per_write_op - average time, measured in microseconds, required to transfer data from the initiator to the array.</li> <li>usec_per_read_op - average time, measured in microseconds, it takes the array to process an I/O read request.</li> <li>usec_per_write_op - average time, measured in microseconds, it takes the array to process an I/O write request.</li> <li>queue_depth - average number of queued I/O requests.</li> </ul> <p><b>IOPS</b></p> <ul style="list-style-type: none"> <li>reads_per_sec - number of read requests processed per second.</li> <li>writes_per_sec - number of write requests processed per second.</li> </ul> <p><b>Bandwidth</b></p> <ul style="list-style-type: none"> <li>input_per_sec - number of bytes written per second.</li> <li>output_per_sec - number of bytes read per second.</li> </ul> <p>Optional.</p> |
| banner         | boolean | <p>Displays the "message of the day" (MOTD) text that is sent to all Purity users. The banner message is displayed in the login pane of the Purity GUI and via SSH after users log in.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| connection_key | boolean | <p>Displays a connection key that can be used to connect to this array.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| controllers    | boolean | <p>Displays the mode and status of each controller on the array. For arrays to which a second controller has never been connected, only a single controller mode is displayed. Once an additional controller has been connected, its information is always shown.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| historical     | string  | <p>If the action parameter is set to monitor, set this parameter to display historical performance data at the specified resolution.</p> <p>If the space parameter is set to true, set this parameter to display historical space data at the specified resolution.</p> <p>Valid historical values are: 1h, 3h, 24h, 7d, 30d, 90d, and 1y.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| idle_timeout   | boolean | <p>Displays the idle time limit, in minutes, of the Purity GUI and CLI sessions. Users are automatically logged out a session that exceeds the idle timeout limit.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |

|              |         |                                                                                                                                                                                             |
|--------------|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| ntpserver    | boolean | Displays the hostnames or IP addresses of the NTP servers currently being used by the array to maintain reference time.<br><br>Optional.                                                    |
| phonehome    | boolean | Displays the current state of the Purity phonehome automatic hourly log transmission facility as enabled or disabled.<br><br>Optional.                                                      |
| proxy        | boolean | Displays the proxy host for the phonehome facility when HTTPS is the phonehome protocol (the phonehome facility itself determines which protocol to use).<br><br>Optional.                  |
| relayhost    | boolean | Displays the hostname or IP address of the electronic mail relay server currently being used as a forwarding point for email alerts generated by the array.<br><br>Optional.                |
| scsi_timeout | boolean | Displays the amount of time (in seconds) that can lapse during an I/O interruption before the target ports log out of the fabric. The default timeout value is 60 seconds.<br><br>Optional. |
| senderdomain | boolean | Displays domain name from which Purity sends email alert messages.<br><br>Optional.                                                                                                         |
| space        | boolean | Displays the amount of usable physical storage on the array and the amount of storage occupied by data and metadata.<br><br>Optional.                                                       |
| syslogserver | boolean | Displays remote syslog servers for delivering notifications.<br><br>Optional.                                                                                                               |

**Example 1: List array attributes**

Request:

```
GET https://pure01.example.com/api/1.11/array
```

Response:

```
{
  "array_name": "pure01",
  "id": "5c77c0fc-1ae5-4c4f-892e-fd424b8a3449",
  "revision": "201703131824+e7d8e89",
  "version": "4.10.1"
}
```

**Example 2: List array controllers**

Request:

```
GET https://pure01.example.com/api/1.11/array?controllers=true
```

Response:

```
[
  {
    "mode": "primary",
    "model": "VMware",
    "name": "CT0",
    "status": "ready",
    "version": "4.10.1"
  }
]
```

```
]
}
```

**Example 3: List array space usage**

Request:

```
GET https://pure01.example.com/api/1.11/array?space=true
```

Response:

```
{
  "capacity": 3770384763,
  "data_reduction": 1.0,
  "hostname": "pure01",
  "parity": 1.0,
  "shared_space": 0,
  "snapshots": 0,
  "system": 0,
  "thin_provisioning": 0.0,
  "total": 0,
  "total_reduction": 1.0,
  "volumes": 0
}
```

**Example 4: List array space usage for the past hour**

Request:

```
GET https://pure01.example.com/api/1.11/array?space=true&historical=1h
```

Response:

```
[
  {
    "capacity": 3770384763,
    "data_reduction": 1.0,
    "hostname": "pure01",
    "parity": null,
    "shared_space": 0,
    "snapshots": 0,
    "system": 0,
    "thin_provisioning": null,
    "time": "2017-03-13T19:40:00Z",
    "total": 0,
    "total_reduction": null,
    "volumes": 0
  },
  {
    "capacity": 3770384763,
    "data_reduction": 1.0,
    "hostname": "pure01",
    "parity": null,
    "shared_space": 0,
    "snapshots": 0,
    "system": 0,
    "thin_provisioning": null,
    "time": "2017-03-13T19:40:30Z",
    "total": 0,
    "total_reduction": null,
    "volumes": 0
  },
  ...
]
```

**Example 5: List real-time performance data for the array**

Request:

```
GET https://pure01.example.com/api/1.11/array?action=monitor
```

Response:

```
[
  {
```

```
    "input_per_sec": 0,
    "output_per_sec": 0,
    "queue_depth": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:19Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  }
]
```

Example 6: List historical performance data for the array at resolution '1h'

Request:

```
GET https://pure01.example.com/api/1.11/array?action=monitor&historical=1h
```

Response:

```
[
  {
    "input_per_sec": 0,
    "output_per_sec": 0,
    "queue_depth": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:40:00Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  },
  {
    "input_per_sec": 0,
    "output_per_sec": 0,
    "queue_depth": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:40:30Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  },
  ...
  {
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  }
]
```

2.2 GET array/connection

Lists connected arrays.

Parameters

| Parameter | Type    | Description                                                                 |
|-----------|---------|-----------------------------------------------------------------------------|
| throttle  | boolean | Displays (true) outgoing bandwidth throttling information.<br><br>Optional. |

Example 1: List connected arrays

Request:

```
GET https://pure01.example.com/api/1.11/array/connection
```

Response:

```
[ ]
```

## 2.3 GET array/console\_lock

Displays the status of the console lock.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Displays the console lock status

Request:

```
GET https://pure01.example.com/api/1.11/array/console_lock
```

Response:

```
{
  "console_lock": "disabled"
}
```

## 2.4 GET array/phonehome

Lists information about the status of the transmission logs for the phonehome facility.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Display phonehome status

Request:

```
GET https://pure01.example.com/api/1.11/array/phonehome
```

Response:

```
{
  "action": null,
  "status": null
}
```

## 2.5 GET array/remoteassist

Lists information about the status (enabled or disabled) of a remote assist session.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Display remoteassist status

Request:

```
GET https://pure01.example.com/api/1.11/array/remoteassist
```

Response:

```
{
  "name": "pure01-ct0",
  "port": "",
  "status": "disabled"
}
```

## 2.6 POST array/connection

Creates a connection between the current array and the specified array.

### Parameters

| Parameter           | Type   | Description                                                                                                     |
|---------------------|--------|-----------------------------------------------------------------------------------------------------------------|
| connection_key      | string | The connection_key of the array to be connected.<br><br>Required.                                               |
| management_address  | string | The management address of the array to be connected.<br><br>Required.                                           |
| replication_address | string | The replication address of the array to be connected.<br><br>Optional.                                          |
| type                | list   | The type(s) of connection desired. The only option supported in this version is 'replication'.<br><br>Required. |

**Example 1: Create a connection between array pure01 and array pure02 for replication purposes.**

Request:

```
POST https://pure01.example.com/api/1.11/array/connection
{
  "connection_key": "$CONNECTION_KEY",
  "management_address": "pure02.example.com",
  "type": [
    "replication"
  ]
}
```

Response:

```
{
  "array_name": "pure02",
  "id": "39a1cbef-299a-4111-a432-ea78a461ece0",
  "management_address": "pure02",
  "replication_address": "pure02",
  "type": [
    "replication"
  ],
  "version": "4.10.1"
}
```

## 2.7 PUT array

Modifies the attributes for the array.

At least one parameter must be specified.

### Parameters

| Parameter    | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|--------------|--------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| banner       | string | <p>Sets a common "message of the day" (MOTD) that is sent to all Purity users. The banner message is displayed in the login pane of the Purity GUI and via SSH after users log in.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| idle_timeout | number | <p>Sets the idle time limit, in minutes, of the Purity GUI and CLI sessions. Valid values are between 5 and 180 minutes. The default timeout value is 30 minutes. Specifying a value of zero disables the automatic log-off feature. Changes made to the <code>idle_timeout</code> value do not apply to existing Purity sessions.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| name         | string | <p>Renames the array.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| ntpserver    | list   | <p>Specifies alternate NTP servers, by IP address or hostname, assigned as the array source for reference time. Supersedes any previous NTP server assignments.</p> <p>If specifying an IP address, for IPv4, specify the IP address in the form <code>ddd.ddd.ddd.ddd</code>, where <code>ddd</code> is a number ranging from 0 to 255 representing a group of 8 bits. For IPv6, specify the IP address in the form <code>xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx</code>, where <code>xxxx</code> is a hexadecimal number representing a group of 16 bits. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon (<code>::</code>).</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| proxy        | string | <p>Sets the proxy host for the phonehome facility when HTTPS is the phonehome protocol (the phonehome facility itself determines which protocol to use). The format for the value is <code>https://HOSTNAME:PORT</code>, where <code>HOSTNAME</code> is the name of the proxy host and <code>PORT</code> is the TCP/IP port number used by the proxy host.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| relayhost    | string | <p>Sets the hostname or IP address of the electronic mail relay server currently being used as a forwarding point for email alerts generated by the array.</p> <p>If specifying an IP address, enter the IPv4 or IPv6 address.</p> <p>For IPv4, specify the IP address in the form <code>ddd.ddd.ddd.ddd</code>, where <code>ddd</code> is a number ranging from 0 to 255 representing a group of 8 bits. If a port number is also specified, append it to the end of the address in the format <code>ddd.ddd.ddd.ddd:PORT</code>, where <code>PORT</code> represents the port number.</p> <p>For IPv6, specify the IP address in the form <code>xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx</code>, where <code>xxxx</code> is a hexadecimal number representing a group of 16 bits. Consecutive fields of zeros can be shortened by replacing the zeros with a double colon (<code>::</code>). If a port number is also specified, enclose the entire address in square brackets (<code>[]</code>) and append the port number to the end of the address. For example, <code>[xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx]:PORT</code>, where <code>PORT</code> represents the port number.</p> <p>Optional.</p> |
| scsi_timeout | number | <p>Changes the amount of time, in seconds, that can lapse during an I/O interruption before the target ports log out of the fabric. The default timeout value is 60 seconds.</p> <p>Changing the default timeout value may cause an initiator to mistakenly interpret the status of the FlashArray as failed or generate a host timeout. Contact the Pure Storage Support team before you change the <code>scsi_timeout</code> value.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| senderdomain | string | <p>Sets the domain name from which Purity sends email alert messages.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| syslogserver | list   | <p>Specifies the remote syslog servers for delivering notifications. For example, <code>tcp://MyHost.com</code>.</p> <p>Specify the URI in the format <code>PROTOCOL://HOSTNAME:PORT</code>.</p> <p><code>PROTOCOL</code> is "tcp", "tls", or "udp".</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

HOSTNAME is the syslog server hostname or IP address. If specifying an IP address, for IPv4, specify the IP address in the form ddd . ddd . ddd . ddd, where ddd is a number ranging from 0 to 255 representing a group of 8 bits. For IPv6, specify the IP address in the form [ xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx ], where xxxx is a hexadecimal number representing a group of 16 bits. Enclose the entire address in square brackets ( [ ] ). Consecutive fields of zeros can be shortened by replacing the zeros with a double colon ( :: ).

PORT is the port at which the server is listening. If a port number is specified, append it to the end of the address. If the port is not specified, it defaults to 514.

Optional.

## 2.8 PUT array/connection/{connection}

Modifies the bandwidth throttling attributes for a connected array.

At least one parameter must be specified.

### Parameters

| Parameter     | Type             | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
|---------------|------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| default_limit | number or string | Default maximum bandwidth threshold for outbound traffic. Once exceeded, bandwidth throttling occurs.<br><br>Enter the size as a number (bytes) or as a string with a single character unit symbol. Valid unit symbols are K, M, G, representing KiB, MiB, GiB, respectively, where "K" denotes 2 <sup>10</sup> , "Mi" denotes 2 <sup>20</sup> , and so on. If the unit symbol is not specified, the unit defaults to bytes.<br><br>Optional.                                      |
| window        | object           | Range of time during which --window_limit threshold is in effect.<br><br>The start and end times must be set on the hour.<br><br>Enter the time range with the start and end attributes, both measured in seconds, where start represents the window start time and end represents the window end time.<br><br>Optional.                                                                                                                                                           |
| window_limit  | number or string | Maximum bandwidth threshold for outbound traffic during the specified window_limit time range. Once exceeded, bandwidth throttling occurs.<br><br>Enter the size as a number (bytes) or as a string with a single character unit symbol. Valid unit symbols are K, M, G, representing KiB, MiB, GiB, respectively, where "K" denotes 2 <sup>10</sup> , "Mi" denotes 2 <sup>20</sup> , and so on. If the unit symbol is not specified, the unit defaults to bytes.<br><br>Optional. |

## 2.9 PUT array/console\_lock

Enables or disables root login through the console.

At least one parameter must be specified.

### Parameters

| Parameter | Type    | Description                                                                                                                                   |
|-----------|---------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| enabled   | boolean | Enables (true) or disables (false) the console lock which prevents the root user from logging in through the system console.<br><br>Optional. |

### Example 1: Enable console lock

Request:

```
PUT https://pure01.example.com/api/1.11/array/console_lock
{
  "enabled": true
}
```

Response:

```
{
  "console_lock": "enabled"
}
```

**Example 2: Disable console lock**

Request:

```
PUT https://pure01.example.com/api/1.11/array/console_lock
{
  "enabled": false
}
```

Response:

```
{
  "console_lock": "disabled"
}
```

**2.10 PUT array/phonehome**

Performs phonehome actions.

At least one parameter must be specified.

**Parameters**

| Parameter | Type    | Description                                                                                                                                                                                                                        |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string  | Transmits event logs stored in the array to the Pure Storage Support team via the phonehome channel. Specify the phonehome log time period as any of the following: send_all, send_today, send_yesterday, cancel.<br><br>Optional. |
| enabled   | boolean | Enables (true) or disables (false) the automatic hourly transmission of array logs to the Pure Storage Support team.<br><br>Optional.                                                                                              |

**Example 1: Enable phonehome**

Request:

```
PUT https://pure01.example.com/api/1.11/array/phonehome
{
  "enabled": true
}
```

Response:

```
{
  "phonehome": "enabled"
}
```

**Example 2: Disable phonehome**

Request:

```
PUT https://pure01.example.com/api/1.11/array/phonehome
{
  "enabled": false
}
```

Response:

```
{
  "phonehome": "disabled"
}
```

## 2.11 PUT array/remoteassist

Enables or disables a remote assist session.

### Parameters

| Parameter | Type   | Description                                                                          |
|-----------|--------|--------------------------------------------------------------------------------------|
| action    | string | Enables ("connect") or disables ("disconnect") a remote assist session.<br>Required. |

## 2.12 DELETE array/connection/{connection}

Disconnects the current array from the specified array.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Disconnect array pure02 from array pure01

Request:

```
DELETE https://pure01.example.com/api/1.11/array/connection/pure02
```

Response:

```
{
  "name": "pure02"
}
```

## 3. Volumes and Snapshots

View and manage volumes and snapshots.

### 3.1 GET volume

Lists volumes and snapshots and their attributes.

Created time is displayed in Greenwich Mean Time (GMT) and size is displayed in bytes.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
|-----------|------|-------------|

|              |         |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|--------------|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action       | string  | <p>If set to <code>monitor</code>, displays real-time or historical performance data. Time is displayed in Greenwich Mean Time (GMT).</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                          |
| connect      | boolean | <p>Displays all host-volume connections, either private or shared, and the LUNs used by the hosts to address the volumes.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                      |
| historical   | string  | <p>If the <code>action</code> parameter is set to <code>monitor</code>, set this parameter to display historical performance data at the specified resolution.</p> <p>If the <code>space</code> parameter is set to <code>true</code>, set this parameter to display historical space data at the specified resolution.</p> <p>Valid historical values are: 1h, 3h, 24h, 7d, 30d, 90d, and 1y.</p> <p>Include the <code>names</code> parameter to only display historical performance or space data for the specified volumes.</p> <p>Optional.</p> |
| names        | list    | <p>Displays specified volumes. Enter multiple volume names in comma-separated format. Volume names can include asterisk (*) wildcard characters to represent zero or more characters.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                          |
| pending      | boolean | <p>Includes (<code>true</code>) destroyed volumes that are in the eradication pending state. Time remaining is displayed in seconds.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                           |
| pending_only | boolean | <p>Lists (<code>true</code>) destroyed volumes that are in the eradication pending state. Time remaining is displayed in seconds.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                              |
| pgrouplist   | list    | <p>Displays specified protection groups or protection group snapshots. Only valid if the <code>snap</code> parameter is set to <code>true</code>. Enter multiple names in comma-separated format. Names can include asterisk (*) wildcard characters to represent zero or more characters.</p> <p>Optional.</p>                                                                                                                                                                                                                                     |
| private      | boolean | <p>Used with the <code>connect</code> parameter to display (<code>true</code>) private host-volume connections.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                |
| protect      | boolean | <p>Displays (<code>true</code>) all protected volumes and their associated protection groups.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| shared       | boolean | <p>Used with the <code>connect</code> parameter to display (<code>true</code>) shared host-volume connections.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                 |
| snap         | boolean | <p>Lists all snapshots (<code>true</code>).</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| space        | boolean | <p>Lists size and space consumption attributes for each volume.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                |

**Example 1: List all volumes**

Request:

GET <https://pure01.example.com/api/1.11/volume>

Response:

```
[
  {
    "created": "2017-03-13T19:42:12Z",
    "name": "v1",
    "serial": "5C77C0FC1AE54C4F00011010",
    "size": 1073741824,
    "source": null
  },
  {
    "created": "2017-03-13T19:42:13Z",
    "name": "v2",
    "serial": "5C77C0FC1AE54C4F00011011",
    "size": 2147483648,
    "source": null
  },
  {
    "created": "2017-03-13T19:42:13Z",
    "name": "v3",
    "serial": "5C77C0FC1AE54C4F00011012",
    "size": 3221225472,
    "source": null
  }
]
```

**Example 2: List all volumes including those pending eradication**

Request:

```
GET https://pure01.example.com/api/1.11/volume?pending=true
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:12Z",
    "name": "v1",
    "serial": "5C77C0FC1AE54C4F00011010",
    "size": 1073741824,
    "source": null,
    "time_remaining": null
  },
  {
    "created": "2017-03-13T19:42:13Z",
    "name": "v2",
    "serial": "5C77C0FC1AE54C4F00011011",
    "size": 2147483648,
    "source": null,
    "time_remaining": null
  },
  {
    "created": "2017-03-13T19:42:13Z",
    "name": "v3",
    "serial": "5C77C0FC1AE54C4F00011012",
    "size": 3221225472,
    "source": null,
    "time_remaining": null
  },
  ...
  {
    "source": null,
    "time_remaining": 86400
  }
]
```

**Example 3: List all volumes pending eradication**

Request:

```
GET https://pure01.example.com/api/1.11/volume?pending_only=true
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:14Z",
    "name": "v4",
    "serial": "5C77C0FC1AE54C4F00011013",
    "size": 4294967296,

```

```

    "source": null,
    "time_remaining": 86400
  }
]

```

**Example 4: List all snapshots**

Request:

```
GET https://pure01.example.com/api/1.11/volume?snap=true
```

Response:

```

[
  {
    "created": "2017-03-13T19:42:14Z",
    "name": "v3.4116",
    "serial": "5C77C0FC1AE54C4F00011014",
    "size": 3221225472,
    "source": "v3"
  },
  {
    "created": "2017-03-13T19:42:15Z",
    "name": "v3.snap1",
    "serial": "5C77C0FC1AE54C4F00011015",
    "size": 3221225472,
    "source": "v3"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg1.monday.v1",
    "serial": "5C77C0FC1AE54C4F00011016",
    "size": 1073741824,
    "source": "v1"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg2.1.v1",
    "size": 1073741824,
    "source": "v1"
  },
  ...
]

```

**Example 5: List per volume space usage**

Request:

```
GET https://pure01.example.com/api/1.11/volume?space=true
```

Response:

```

[
  {
    "data_reduction": 1.0,
    "name": "v1",
    "shared_space": null,
    "size": 1073741824,
    "snapshots": 0,
    "system": null,
    "thin_provisioning": 1.0,
    "total": 0,
    "total_reduction": 1.0,
    "volumes": 0
  },
  {
    "data_reduction": 1.0,
    "name": "v2",
    "shared_space": null,
    "size": 2147483648,
    "snapshots": 0,
    "system": null,
    "thin_provisioning": 1.0,
    "total": 0,
    "total_reduction": 1.0,
    "volumes": 0
  },
  ...
]

```

]

**Example 6:** List all volume snapshots that were created as part of protection group snapshots for protection groups pg1 and pg2.

Request:

```
GET https://pure01.example.com/api/1.11/volume?snap=true&pgrouplist=pg1,pg2
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg1.monday.v1",
    "serial": "5C77C0FC1AE54C4F00011016",
    "size": 1073741824,
    "source": "v1"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg2.1.v1",
    "serial": "5C77C0FC1AE54C4F00011017",
    "size": 1073741824,
    "source": "v1"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg1.2.v1",
    "serial": "5C77C0FC1AE54C4F00011018",
    "size": 1073741824,
    "source": "v1"
  }
]
```

### 3.2 GET volume/{volume}

Lists the attributes for the specified volume or snapshot.

If listing volume snapshot attributes, the snap parameter must be specified.

#### Parameters

| Parameter    | Type    | Description                                                                                                                                                                                                                                                                                                                                              |
|--------------|---------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action       | string  | If set to monitor, displays real-time or historical performance data. Time is displayed in Greenwich Mean Time (GMT).<br><br>Optional.                                                                                                                                                                                                                   |
| historical   | string  | If the action parameter is set to monitor, set this parameter to display historical performance data at the specified resolution.<br><br>If the space parameter is set to true, set this parameter to display historical space data at the specified resolution.<br><br>Valid historical values are: 1h, 3h, 24h, 7d, 30d, 90d, and 1y.<br><br>Optional. |
| pending      | boolean | If the volume is in the eradication pending state, set pending to true to display the attributes for the destroyed volume.<br><br>Optional.                                                                                                                                                                                                              |
| pending_only | boolean | Lists (true) destroyed volumes that are in the eradication pending state and their attributes.<br><br>Optional.                                                                                                                                                                                                                                          |
| pgrouplist   | list    | Displays specified protection groups or protection group snapshots. Only valid if snap is true. Only valid if the snap parameter is set to true. Enter multiple names in comma-separated format. Names can include asterisk (*) wildcard characters to represent zero or more characters.                                                                |

|         |         |                                                                                                                                                                                                 |
|---------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|         |         | Optional.                                                                                                                                                                                       |
| protect | boolean | Displays (true) the names of all protection groups associated with the specified volume. If the volume is not protected, returns an empty response.                                             |
|         |         | Optional.                                                                                                                                                                                       |
| snap    | boolean | If listing the attributes for a specified volume, set snap to true to list all snapshots within the volume. If listing the attributes for a specified volume snapshot, always set snap to true. |
|         |         | Optional if listing attributes for a specified volume. Required if listing attributes for a specified volume snapshot.                                                                          |
| space   | boolean | Lists size and space consumption attributes for the specified volume.                                                                                                                           |
|         |         | Optional.                                                                                                                                                                                       |

**Example 1: List details for volume v1**

Request:

```
GET https://pure01.example.com/api/1.11/volume/v1
```

Response:

```
{
  "created": "2017-03-13T19:42:12Z",
  "name": "v1",
  "serial": "5C77C0FC1AE54C4F00011010",
  "size": 1073741824,
  "source": null
}
```

**Example 2: List snapshots of volume v3**

Request:

```
GET https://pure01.example.com/api/1.11/volume/v3?snap=true
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:14Z",
    "name": "v3.4116",
    "serial": "5C77C0FC1AE54C4F00011014",
    "size": 3221225472,
    "source": "v3"
  },
  {
    "created": "2017-03-13T19:42:15Z",
    "name": "v3.snap1",
    "serial": "5C77C0FC1AE54C4F00011015",
    "size": 3221225472,
    "source": "v3"
  }
]
```

**Example 3: List real-time performance data for volume v3.**

Request:

```
GET https://pure01.example.com/api/1.11/volume/v3?action=monitor
```

Response:

```
[
  {
    "input_per_sec": 0,
    "name": "v3",
  }
]
```

```

    "output_per_sec": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:23Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  }
]

```

**Example 4: List volume snapshots of v1 that were created as part of protection group snapshots for protection groups pg1 and pg2.**

Request:

```
GET https://pure01.example.com/api/1.11/volume/v1?snap=true&pgrouplist=pg1,pg2
```

Response:

```

[
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg1.monday.v1",
    "serial": "5C77C0FC1AE54C4F00011016",
    "size": 1073741824,
    "source": "v1"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg2.1.v1",
    "serial": "5C77C0FC1AE54C4F00011017",
    "size": 1073741824,
    "source": "v1"
  },
  {
    "created": "2017-03-13T19:42:17Z",
    "name": "pg1.2.v1",
    "serial": "5C77C0FC1AE54C4F00011018",
    "size": 1073741824,
    "source": "v1"
  }
]

```

### 3.3 GET volume/{volume}/diff

Lists block differences for the specified volume snapshot.

#### Parameters

| Parameter  | Type             | Description                                                                                                                                             |
|------------|------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------|
| base       | string           | Snapshot name to be used as the base for the diff. If a base snapshot is not specified, all mapped blocks for the volume are returned.<br><br>Optional. |
| block_size | number or string | Granularity, in bytes, at which to compare.<br><br>Required.                                                                                            |
| length     | number or string | Length of the region, in bytes, to compare.<br><br>Required.                                                                                            |
| offset     | number or string | Absolute offset, in bytes, of the region to compare. Must be a multiple of block_size.<br><br>Optional.                                                 |

**Example 1: List all block differences for volume snapshot v3.snap1 with a block size of 512 bytes and a length of 2 gigabytes.**

Request:

```
GET https://pure01.example.com/api/1.11/volume/v3.snap1/diff?block_size=512&length=2G
```

Response:

```
[ ]
```

### 3.4 GET volume/{volume}/hgroup

Lists shared connections for the specified volume.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

#### Example 1: List shared connections for volume v2

Request:

```
GET https://pure01.example.com/api/1.11/volume/v2/hgroup
```

Response:

```
[
  {
    "hgroup": "hg2",
    "host": null,
    "lun": 15,
    "name": "v2",
    "size": 2147483648
  }
]
```

### 3.5 GET volume/{volume}/host

Lists private connections for the specified volume.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

#### Example 1: List private connections for volume v3

Request:

```
GET https://pure01.example.com/api/1.11/volume/v3/host
```

Response:

```
[
  {
    "host": "h2",
    "lun": 7,
    "name": "v3",
    "size": 3221225472
  }
]
```

### 3.6 POST volume/{volume}

Creates a volume or copies a volume or snapshot.

Either the size or source parameter must be specified.

#### Parameters

| Parameter | Type             | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
|-----------|------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| overwrite | boolean          | When used with source, overwrites (true) an existing volume.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                         |
| size      | number or string | Creates a volume with the specified provisioned size.<br><br>Enter the size as a number (bytes) or as a string with a single character unit symbol. Valid unit symbols are K, M, G, T, P, representing KiB, MiB, GiB, TiB, and PiB, respectively, where "Ki" denotes 2 <sup>10</sup> , "Mi" denotes 2 <sup>20</sup> , and so on. If the unit symbol is not specified, the unit defaults to bytes.<br><br>Optional.                                                                    |
| source    | string           | Copies a volume or snapshot to create a new volume or replace an existing one. Specify the name of a volume or snapshot whose data is copied to the volume specified.<br><br>If the volume or snapshot replaces an existing volume, the overwrite parameter must also be specified. If the volume or snapshot replaces an existing volume, an undo snapshot is automatically taken (providing a 24-hour window during which the previous contents can be retrieved).<br><br>Optional. |

#### Example 1: Create a new volume

Request:

```
POST https://pure01.example.com/api/1.11/volume/v5
{
  "size": "5G"
}
```

Response:

```
{
  "created": "2017-03-13T19:42:24Z",
  "name": "v5",
  "serial": "5C77C0FC1AE54C4F0001101D",
  "size": 5368709120,
  "source": null
}
```

#### Example 2: Create v6 by copying v1

Request:

```
POST https://pure01.example.com/api/1.11/volume/v6
{
  "source": "v1"
}
```

Response:

```
{
  "created": "2017-03-13T19:42:25Z",
  "name": "v6",
  "serial": "5C77C0FC1AE54C4F0001101E",
  "size": 1073741824,
  "source": "v1"
}
```

Example 3: Overwrite v6 by copying v1

Request:

```
POST https://pure01.example.com/api/1.11/volume/v6
{
  "overwrite": true,
  "source": "v1"
}
```

Response:

```
{
  "created": "2017-03-13T19:42:26Z",
  "name": "v6",
  "serial": "5C77C0FC1AE54C4F0001101E",
  "size": 1073741824,
  "source": "v1"
}
```

3.7 POST volume

Creates snapshots of one or more volumes.

Parameters

| Parameter | Type    | Description                                                                       |
|-----------|---------|-----------------------------------------------------------------------------------|
| snap      | boolean | Must be set to true to signify that a snapshot is being created.<br><br>Required. |
| source    | list    | Names of one or more volumes to snapshot.<br><br>Required.                        |
| suffix    | string  | Specify a custom suffix that is added to the snapshot name.<br><br>Optional.      |

Example 1: Create snapshots of v5 and v6

Request:

```
POST https://pure01.example.com/api/1.11/volume
{
  "snap": true,
  "source": [
    "v5",
    "v6"
  ]
}
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:26Z",
    "name": "v5.4128",
    "serial": "5C77C0FC1AE54C4F00011020",
    "size": 5368709120,
    "source": "v5"
  },
  {
    "created": "2017-03-13T19:42:26Z",
    "name": "v6.4129",
    "serial": "5C77C0FC1AE54C4F00011021",
    "size": 1073741824,
    "source": "v6"
  }
]
```

**Example 2: Create snapshots of v5 and v6 with a custom suffix**

Request:

```
POST https://pure01.example.com/api/1.11/volume
{
  "snap": true,
  "source": [
    "v5",
    "v6"
  ],
  "suffix": "crackle"
}
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:26Z",
    "name": "v5.crackle",
    "serial": "5C77C0FC1AE54C4F00011022",
    "size": 5368709120,
    "source": "v5"
  },
  {
    "created": "2017-03-13T19:42:26Z",
    "name": "v6.crackle",
    "serial": "5C77C0FC1AE54C4F00011023",
    "size": 1073741824,
    "source": "v6"
  }
]
```

**3.8 POST volume/{volume}/pgroup/{pgroup}**

Adds a volume to a protection group.

You can only add members of the same object type to a protection group. For example, you cannot add hosts or host groups to a protection group that contains volumes.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**3.9 PUT volume/{volume}**

Recovers and renames the specified volume or volume snapshot, or resizes the specified volume.

Either the size, action or name parameter must be specified.

**Parameters**

| Parameter | Type             | Description                                                                                                                                                                                                                                                                   |
|-----------|------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string           | Recovers the contents of the specified volume or volume snapshot. Set the parameter to recover.<br><br>Optional.                                                                                                                                                              |
| name      | string           | Renames the specified volume or volume snapshot.<br><br>When renaming a snapshot, only the suffix can be changed.<br><br>Optional.                                                                                                                                            |
| size      | number or string | Changes the provisioned size of the volume. If the new volume size is smaller than the original, then the truncate parameter needs to be set to true.<br><br>Enter the size as a number (bytes) or as a string with a single character unit symbol. Valid unit symbols are K, |

M, G, T, P, representing KiB, MiB, GiB, TiB, and PiB, respectively, where "Ki" denotes 2<sup>10</sup>, "Mi" denotes 2<sup>20</sup>, and so on. If the unit symbol is not specified, the unit defaults to bytes.

Optional.

|          |         |                                                                                                                                                                                                                                                                                                                             |
|----------|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| truncate | boolean | Truncates (true) the volume. When a volume is truncated, Purity automatically takes an undo snapshot, providing a 24-hour window during which the previous contents can be retrieved. After truncating a volume, its provisioned size can be subsequently increased, but the data in truncated sectors cannot be retrieved. |
|          |         | Required if the volume size is set to a size that is smaller than the original.                                                                                                                                                                                                                                             |

#### Example 1: Set the provisioned size for volume v5 to 10G

Request:

```
PUT https://pure01.example.com/api/1.11/volume/v5
{
  "size": "10G"
}
```

Response:

```
{
  "name": "v5",
  "size": 10737418240
}
```

#### Example 2: Truncate volume v5 to 1073741824 bytes

Request:

```
PUT https://pure01.example.com/api/1.11/volume/v5
{
  "size": 1073741824,
  "truncate": true
}
```

Response:

```
{
  "name": "v5",
  "size": 1073741824
}
```

#### Example 3: Rename volume v5 to v5\_renamed

Request:

```
PUT https://pure01.example.com/api/1.11/volume/v5
{
  "name": "v5_renamed"
}
```

Response:

```
{
  "name": "v5_renamed"
}
```

#### Example 4: Rename suffix of volume snapshot v5.snap from snap to snap2

Request:

```
PUT https://pure01.example.com/api/1.11/volume/v3.snap1
{
  "name": "v3.snap2"
}
```

```
}

```

Response:

```
{
  "name": "v3.snap2"
}
```

### 3.10 DELETE volume/{volume}

Destroys or eradicates the specified volume or snapshot.

#### Parameters

| Parameter | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
|-----------|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| eradicate | boolean | <p>If set to <code>true</code>, eradicates the specified volume or snapshot. If destroying or eradicating a volume, its snapshots are also destroyed or eradicated.</p> <p>After destroying a volume or snapshot, you can eradicate it to immediately terminate the 24-hour eradication period and begin storage reclamation. Once eradication has begun, the volume or snapshot can no longer be recovered.</p> <p>If set to <code>false</code>, destroys the specified volume or snapshot. The destroyed volume or snapshot undergoes a 24-hour eradication pending period during which time the volume or snapshot and its data can be fully recovered. After the 24-hour pending period, Purity eradicates the destroyed volume or snapshot.</p> <p>Optional.</p> |

#### Example 1: Destroy volume v6

Request:

```
DELETE https://pure01.example.com/api/1.11/volume/v6

```

Response:

```
{
  "name": "v6"
}
```

#### Example 2: Eradicate volume v6

Request:

```
DELETE https://pure01.example.com/api/1.11/volume/v6?eradicate=true

```

Response:

```
{
  "name": "v6"
}
```

### 3.11 DELETE volume/{volume}/pgroup/{pgroup}

Removes a volume member from a protection group.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
|-----------|------|-------------|

|      |     |     |
|------|-----|-----|
| None | n/a | n/a |
|------|-----|-----|

## 4. Hosts

View, create, and manage hosts.

### 4.1 GET host

Lists all hosts on the array.

#### Parameters

| Parameter   | Type    | Description                                                                                                                                                                                                                                            |
|-------------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action      | string  | If set to <code>monitor</code> , displays host-wide I/O performance information in real time. Time is displayed in Greenwich Mean Time (GMT).<br><br>Optional.                                                                                         |
| all         | boolean | Displays all visible attributes of the specified hosts, including associated worldwide names, host groups, connected volumes and the LUNs used to address them, and array port worldwide names through which the volumes are visible.<br><br>Optional. |
| chap        | boolean | Displays host and target user names and indicates whether host and target passwords have been set.<br><br>Optional.                                                                                                                                    |
| connect     | boolean | Displays all host-volume connections, either private or shared, and the LUNs used by the hosts to address the volumes.<br><br>Optional.                                                                                                                |
| names       | list    | Displays specified hosts. Enter multiple host names in comma-separated format. Host names can include asterisk (*) wildcard characters to represent zero or more characters.<br><br>Optional.                                                          |
| personality | boolean | Displays the personality setting associated with the specified hosts.<br><br>Optional.                                                                                                                                                                 |
| private     | boolean | Used with the <code>connect</code> parameter to display ( <code>true</code> ) private host-volume connections.<br><br>Optional.                                                                                                                        |
| protect     | boolean | Displays all protected hosts and their associated protection groups.<br><br>Optional.                                                                                                                                                                  |
| shared      | boolean | Used with the <code>connect</code> parameter to display ( <code>true</code> ) shared host-volume connections.<br><br>Optional.                                                                                                                         |
| space       | boolean | Displays information about provisioned (virtual) size and physical storage consumption for each volume connected to the specified hosts.<br><br>Optional.                                                                                              |

#### Example 1: List all hosts

Request:

```
GET https://pure01.example.com/api/1.11/host
```

Response:

```
[
  {
    "hgroup": "hg1",
    "iqn": [],
    "name": "h1",
    "wwn": [
      "0000111122223333"
    ]
  },
  {
    "hgroup": "hg1",
    "iqn": [],
    "name": "h2",
    "wwn": []
  },
  {
    "hgroup": null,
    "iqn": [],
    "name": "h3",
    "wwn": []
  }
]
```

Example 2: Display I/O performance for all hosts

Request:

```
GET https://pure01.example.com/api/1.11/host?action=monitor
```

Response:

```
[
  {
    "input_per_sec": 0,
    "name": "h1",
    "output_per_sec": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:27Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  },
  {
    "input_per_sec": 0,
    "name": "h2",
    "output_per_sec": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:27Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  },
  ...
  {
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  }
]
```

4.2 GET host/{host}

Lists the attributes for the specified host.

Parameters

| Parameter | Type    | Description                                                                                                                                      |
|-----------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string  | If set to monitor, displays host-wide I/O performance information in real time. Time is displayed in Greenwich Mean Time (GMT).<br><br>Optional. |
| all       | boolean | Displays all visible attributes of the specified host. Display includes associated worldwide names, host groups,                                 |

connected volumes and the LUNs used to address them, array port worldwide names through which the volumes are visible.

Optional.

|             |         |                                                                                                                                                           |
|-------------|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|
| chap        | boolean | Displays host and target usernames and indicates whether host and target passwords have been set.<br><br>Optional.                                        |
| personality | boolean | Displays the personality setting associated with the specified host.<br><br>Optional.                                                                     |
| protect     | boolean | Displays the names of all protection groups associated with the specified host. If the host is not protected, returns an empty response.<br><br>Optional. |
| space       | boolean | Displays information about provisioned (virtual) size and physical storage consumption for each volume connected to the specified host.<br><br>Optional.  |

#### Example 1: List space usage for host h1

Request:

```
GET https://pure01.example.com/api/1.11/host/h1?space=true
```

Response:

```
{
  "data_reduction": 1.0,
  "name": "h1",
  "size": 1073741824,
  "snapshots": 0,
  "thin_provisioning": 1.0,
  "total": 0,
  "total_reduction": 1.0,
  "volumes": 0
}
```

#### Example 2: List CHAP attributes for host h1

Request:

```
GET https://pure01.example.com/api/1.11/host/h1?chap=true
```

Response:

```
{
  "host_password": null,
  "host_user": null,
  "name": "h1",
  "target_password": null,
  "target_user": null
}
```

#### Example 3: List personality attribute for host h1

Request:

```
GET https://pure01.example.com/api/1.11/host/h1?personality=true
```

Response:

```
{
```

```
{
  "name": "h1",
  "personality": null
}
```

#### Example 4: Display I/O performance for host h1

Request:

```
GET https://pure01.example.com/api/1.11/host/h1?action=monitor
```

Response:

```
{
  "input_per_sec": 0,
  "name": "h1",
  "output_per_sec": 0,
  "reads_per_sec": 0,
  "san_usec_per_read_op": 0,
  "san_usec_per_write_op": 0,
  "time": "2017-03-13T19:42:28Z",
  "usec_per_read_op": 0,
  "usec_per_write_op": 0,
  "writes_per_sec": 0
}
```

### 4.3 GET host/{host}/volume

Lists volumes associated with the specified host and the LUNs used to address them.

#### Parameters

| Parameter | Type    | Description                                                                         |
|-----------|---------|-------------------------------------------------------------------------------------|
| private   | boolean | Restricts (true) the display list to volumes with private connections.<br>Optional. |
| shared    | boolean | Restricts (true) the display list to volumes with shared connections.<br>Optional.  |

#### Example 1: List private and shared connections for host h2

Request:

```
GET https://pure01.example.com/api/1.11/host/h2/volume
```

Response:

```
[
  {
    "hgroup": "hg1",
    "lun": 254,
    "name": "h2",
    "vol": "v1"
  },
  {
    "hgroup": null,
    "lun": 7,
    "name": "h2",
    "vol": "v3"
  }
]
```

#### Example 2: List private connections for host h2

Request:

```
GET https://pure01.example.com/api/1.11/host/h2/volume?private=true
```

Response:

```
[
  {
    "lun": 7,
    "name": "h2",
    "vol": "v3"
  }
]
```

### Example 3: List shared connections for host h2

Request:

```
GET https://pure01.example.com/api/1.11/host/h2/volume?shared=true
```

Response:

```
[
  {
    "hgroup": "hg1",
    "lun": 254,
    "name": "h2",
    "vol": "v1"
  }
]
```

## 4.4 POST host/{host}

Creates a host with the specified name.

### Parameters

| Parameter | Type | Description                                                                          |
|-----------|------|--------------------------------------------------------------------------------------|
| iqnlist   | list | Sets the list of iSCSI qualified names (IQNs) for the new host.<br>Optional.         |
| wwnlist   | list | Sets the list of Fibre Channel worldwide names (WWNs) for the new host.<br>Optional. |

### Example 1: Create host h4 with one wwn

Request:

```
POST https://pure01.example.com/api/1.11/host/h4
{
  "wwnlist": [
    "0000999900009999"
  ]
}
```

Response:

```
{
  "iqn": [],
  "name": "h4",
  "wwn": [
    "0000999900009999"
  ]
}
```

## 4.5 POST host/{host}/pgroup/{pgroup}

Adds a host to a protection group.

You can only add members of the same object type to a protection group. For example, you cannot add hosts or host groups to a protection group that contains volumes.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### 4.6 POST host/{host}/volume/{volume}

Connects a volume to the host.

#### Parameters

| Parameter | Type   | Description                                                                                                                                |
|-----------|--------|--------------------------------------------------------------------------------------------------------------------------------------------|
| lun       | number | Assigns the same LUN to each connection. The connection fails for any host for which the specified LUN is already in use.<br><br>Optional. |

#### Example 1: Create a private connection between host h4 and volume v5\_renamed

Request:

```
POST https://pure01.example.com/api/1.11/host/h4/volume/v5_renamed
```

Response:

```
{
  "lun": 1,
  "name": "h4",
  "vol": "v5_renamed"
}
```

### 4.7 PUT host/{host}

Modifies the attributes for the host.

At least one parameter must be specified.

#### Parameters

| Parameter     | Type   | Description                                                                                   |
|---------------|--------|-----------------------------------------------------------------------------------------------|
| addiqnlist    | list   | Adds the list of iSCSI qualified names (IQNs) to the specified host.<br><br>Optional.         |
| addwwnlist    | list   | Adds the list of Fibre Channel worldwide names (WWNs) to the specified host.<br><br>Optional. |
| host_password | string | Sets the host password for CHAP authentication.<br><br>Optional.                              |
| host_user     | string | Sets the host user name for CHAP authentication.<br><br>Optional.                             |

|                 |        |                                                                                                                                                                                                                       |
|-----------------|--------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| iqnlist         | list   | Assigns a list of iSCSI qualified names (IQNs) to the specified host.<br><br>Optional.                                                                                                                                |
| name            | string | Changes the name of the host to the specified name.<br><br>Optional.                                                                                                                                                  |
| personality     | string | Determines the way in which the host personality tunes the protocol used between the array and the initiator. If the host is running the HP-UX operating system, set the host personality to 'hpux'.<br><br>Optional. |
| remiqnlist      | list   | Removes the list of iSCSI qualified names (IQNs) from the specified host.<br><br>Optional.                                                                                                                            |
| remwwnlist      | list   | Removes the list of Fibre Channel worldwide names (WWNs) from the specified host.<br><br>Optional.                                                                                                                    |
| target_password | string | Sets the target password for CHAP authentication.<br><br>Optional.                                                                                                                                                    |
| target_user     | string | Sets the target user name for CHAP authentication.<br><br>Optional.                                                                                                                                                   |
| wwnlist         | list   | Assigns a list of Fibre Channel worldwide names (WWNs) to the specified host.<br><br>Optional.                                                                                                                        |

**Example 1: Replace list of wwns**

Request:

```
PUT https://pure01.example.com/api/1.11/host/h4
{
  "wwnlist": [
    "1111222233334444",
    "2222333344445555"
  ]
}
```

Response:

```
{
  "hgroup": null,
  "iqn": [],
  "name": "h4",
  "wwn": [
    "1111222233334444",
    "2222333344445555"
  ]
}
```

**Example 2: Add two more wwns to list**

Request:

```
PUT https://pure01.example.com/api/1.11/host/h4
{
  "addwwnlist": [
    "4444333322221111",
    "5555444433332222"
  ]
}
```

Response:

```
{
  "hgroup": null,
  "iqn": [],
  "name": "h4",
  "wwn": [
    "1111222233334444",
    "2222333344445555",
    "4444333322221111",
    "5555444433332222"
  ]
}
```

**Example 3: Remove one wwn from list**

Request:

```
PUT https://pure01.example.com/api/1.11/host/h4
{
  "remwwnlist": [
    "2222333344445555"
  ]
}
```

Response:

```
{
  "hgroup": null,
  "iqn": [],
  "name": "h4",
  "wwn": [
    "1111222233334444",
    "4444333322221111",
    "5555444433332222"
  ]
}
```

**Example 4: Rename a host**

Request:

```
PUT https://pure01.example.com/api/1.11/host/h4
{
  "name": "h5"
}
```

Response:

```
{
  "name": "h5"
}
```

**4.8 DELETE host/{host}/pgroup/{pgroup}**

Removes a host member from a protection group.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**4.9 DELETE host/{host}/volume/{volume}**

Breaks the connection between a host and volume.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
|-----------|------|-------------|

|      |     |     |
|------|-----|-----|
| None | n/a | n/a |
|------|-----|-----|

**Example 1: Disconnect host h5 and volume v5\_renamed**

Request:

```
DELETE https://pure01.example.com/api/1.11/host/h5/volume/v5_renamed
```

Response:

```
{
  "name": "h5",
  "vol": "v5_renamed"
}
```

**4.10 DELETE host/{host}**

Removes the specified host.

Hosts cannot be deleted while they have private connections to volumes or while they are associated with host groups.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: Delete host h5**

Request:

```
DELETE https://pure01.example.com/api/1.11/host/h5
```

Response:

```
{
  "name": "h5"
}
```

**5. Host Groups**

View, create, and manage host groups.

**5.1 GET hgroup**

Lists or monitors all host groups.

**Parameters**

| Parameter | Type    | Description                                                                                                                                                                                    |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string  | If set to monitor, displays host group I/O performance information for all host groups.<br>Optional.                                                                                           |
| connect   | boolean | Displays all volumes associated with host groups, and the LUNs used by the associated hosts to address them.<br>Optional.                                                                      |
| names     | list    | Displays specified host groups. Enter multiple host group names in comma-separated format. Host group names can include asterisk (*) wildcard characters to represent zero or more characters. |

|         |         |                                                                                                            |
|---------|---------|------------------------------------------------------------------------------------------------------------|
|         |         | Optional.                                                                                                  |
| protect | boolean | Displays (true) all protected host groups and their associated protection groups.                          |
|         |         | Optional.                                                                                                  |
| space   | boolean | Displays size and space consumption information for each volume associated with each specified host group. |
|         |         | Optional.                                                                                                  |

**Example 1: List all host groups**

Request:

```
GET https://pure01.example.com/api/1.11/hgroup
```

Response:

```
[
  {
    "hosts": [
      "h1",
      "h2"
    ],
    "name": "hg1"
  },
  {
    "hosts": [],
    "name": "hg2"
  }
]
```

**Example 2: List all host groups' space usage**

Request:

```
GET https://pure01.example.com/api/1.11/hgroup?space=true
```

Response:

```
[
  {
    "data_reduction": 1.0,
    "name": "hg1",
    "size": 1073741824,
    "snapshots": 0,
    "thin_provisioning": 1.0,
    "total": 0,
    "total_reduction": 1.0,
    "volumes": 0
  },
  {
    "data_reduction": 1.0,
    "name": "hg2",
    "size": 2147483648,
    "snapshots": 0,
    "thin_provisioning": 1.0,
    "total": 0,
    "total_reduction": 1.0,
    "volumes": 0
  }
]
```

**Example 3: Monitor I/O performance of all host groups**

Request:

```
GET https://pure01.example.com/api/1.11/hgroup?action=monitor
```

Response:

```
[
  {
    "input_per_sec": 0,
    "name": "hg2",
    "output_per_sec": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:31Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  },
  {
    "input_per_sec": 0,
    "name": "hg1",
    "output_per_sec": 0,
    "reads_per_sec": 0,
    "san_usec_per_read_op": 0,
    "san_usec_per_write_op": 0,
    "time": "2017-03-13T19:42:31Z",
    "usec_per_read_op": 0,
    "usec_per_write_op": 0,
    "writes_per_sec": 0
  }
]
```

## 5.2 GET hgroup/{hgroup}

Lists or monitors a single host group.

### Parameters

| Parameter | Type    | Description                                                                                                                                                                  |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string  | If set to monitor, displays host group I/O performance information for the specified host group.<br><br>Optional.                                                            |
| protect   | boolean | Displays (true) the names of all protection groups associated with the specified host group. If the host group is not protected, returns an empty response.<br><br>Optional. |
| space     | boolean | Displays size and space consumption information for each volume associated with the specified host group.<br><br>Optional.                                                   |

### Example 1: List host group hg1

Request:

```
GET https://pure01.example.com/api/1.11/hgroup/hg1
```

Response:

```
{
  "hosts": [
    "h1",
    "h2"
  ],
  "name": "hg1"
}
```

### Example 2: List space usage for host group hg1

Request:

```
GET https://pure01.example.com/api/1.11/hgroup/hg1?space=true
```

Response:

```
{
  "data_reduction": 1.0,
  "name": "hg1",
  "size": 1073741824,
  "snapshots": 0,
  "thin_provisioning": 1.0,
  "total": 0,
  "total_reduction": 1.0,
  "volumes": 0
}
```

### Example 3: Monitor I/O performance for host group hg1

Request:

```
GET https://pure01.example.com/api/1.11/hgroup/hg1?action=monitor
```

Response:

```
{
  "input_per_sec": 0,
  "name": "hg1",
  "output_per_sec": 0,
  "reads_per_sec": 0,
  "san_usec_per_read_op": 0,
  "san_usec_per_write_op": 0,
  "time": "2017-03-13T19:42:31Z",
  "usec_per_read_op": 0,
  "usec_per_write_op": 0,
  "writes_per_sec": 0
}
```

## 5.3 GET hgroup/{hgroup}/volume

Lists volumes associated with the specified host groups and the LUNs used to address them.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: List volumes connected to host group hg1

Request:

```
GET https://pure01.example.com/api/1.11/hgroup/hg1/volume
```

Response:

```
[
  {
    "lun": 254,
    "name": "hg1",
    "vol": "v1"
  }
]
```

## 5.4 POST hgroup/{hgroup}

Creates a host group with the specified name.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
|-----------|------|-------------|

|          |      |                       |
|----------|------|-----------------------|
| hostlist | list | List of member hosts. |
|          |      | Optional.             |

**Example 1: Create host group hg3**

Request:

```
POST https://pure01.example.com/api/1.11/hgroup/hg3
```

Response:

```
{
  "hosts": [],
  "name": "hg3"
}
```

**5.5 POST hgroup/{hgroup}/pgroup/{pgroup}**

Adds a host group to a protection group.

You can only add members of the same object type to a protection group. For example, you cannot add hosts or host groups to a protection group that contains volumes.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**5.6 POST hgroup/{hgroup}/volume/{volume}**

Connects a volume to all hosts in the specified host group.

If the LUN is not specified, when the volume is connected to the host group, Purity assigns the same LUN to each connection. All hosts in the group use this LUN to communicate with the volume.

**Parameters**

| Parameter | Type   | Description                                                    |
|-----------|--------|----------------------------------------------------------------|
| lun       | number | Assigns the specified LUN to each connection.<br><br>Optional. |

**Example 1: Connect volume v3 to host group hg3**

Request:

```
POST https://pure01.example.com/api/1.11/hgroup/hg3/volume/v3
```

Response:

```
{
  "lun": 254,
  "name": "hg3",
  "vol": "v3"
}
```

**5.7 PUT hgroup/{hgroup}**

Adds, removes, or modifies host members of the host group.

At least one parameter must be specified.

## Parameters

| Parameter   | Type   | Description                                                                |
|-------------|--------|----------------------------------------------------------------------------|
| addhostlist | list   | Adds a list of hosts to the existing list.<br><br>Optional.                |
| hostlist    | list   | Replaces the list of member hosts.<br><br>Optional.                        |
| name        | string | Changes the name of the host group to the specified name.<br><br>Optional. |
| remhostlist | list   | Removes the list of hosts from the existing list.<br><br>Optional.         |

### Example 1: Rename host group

Request:

```
PUT https://pure01.example.com/api/1.11/hgroup/hg3
{
  "name": "hg4"
}
```

Response:

```
{
  "hosts": [],
  "name": "hg4"
}
```

### Example 2: Set host members for hgroup hg4

Request:

```
PUT https://pure01.example.com/api/1.11/hgroup/hg4
{
  "hostlist": [
    "h3"
  ]
}
```

Response:

```
{
  "hosts": [
    "h3"
  ],
  "name": "hg4"
}
```

### Example 3: Remove host members

Request:

```
PUT https://pure01.example.com/api/1.11/hgroup/hg4
{
  "remhostlist": [
    "h3"
  ]
}
```

```
}

```

Response:

```
{
  "hosts": [],
  "name": "hg4"
}

```

## 5.8 DELETE hgroup/{hgroup}/pgroup/{pgroup}

Removes a host group member from a protection group.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 5.9 DELETE hgroup/{hgroup}/volume/{volume}

Breaks the connections between all hosts associated with the host group and the specified volume.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Disconnect volume v3 from host group hg4

Request:

```
DELETE https://pure01.example.com/api/1.11/hgroup/hg4/volume/v3

```

Response:

```
{
  "name": "hg4",
  "vol": "v3"
}

```

## 5.10 DELETE hgroup/{hgroup}

Deletes the specified host group. You must disconnect all volumes and remove all hosts from the host group before deleting the host group.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Delete host group hg4

Request:

```
DELETE https://pure01.example.com/api/1.11/hgroup/hg4

```

Response:

```
{
  "name": "hg4"
}
```

## 6. Protection Groups

View, create, and manage protection groups.

### 6.1 GET pgroup

Lists protection groups and protection group snapshots and their attributes.

#### Parameters

| Parameter    | Type    | Description                                                                                                                                                                                                                                                                                           |
|--------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| names        | list    | Displays specified protection groups. Enter multiple protection group names in comma-separated format. Protection group names can include asterisk (*) wildcard characters to represent zero or more characters.<br><br>Optional.                                                                     |
| pending      | boolean | Includes (true) destroyed protection groups that are in the eradication pending state. Time remaining is displayed in seconds. The pending option can also be used with the schedule, retention, space, or snap options to include a list of pending protection groups or snapshots.<br><br>Optional. |
| pending_only | boolean | Lists (true) destroyed protection groups that are in the eradication pending state. Time remaining is displayed in seconds. The pending option can also be used with the schedule, retention, space, or snap options to include a list of pending protection groups or snapshots.<br><br>Optional.    |
| retention    | boolean | Displays (true) the source/target retention policy.<br><br>Optional.                                                                                                                                                                                                                                  |
| schedule     | boolean | Displays (true) the snapshot/replication schedule.<br><br>Optional.                                                                                                                                                                                                                                   |
| snap         | boolean | Lists all snapshots (true). Can be used with the space parameter to list space consumption for all snapshots.<br><br>Optional.                                                                                                                                                                        |
| source       | boolean | Lists (true) protection groups and snapshots created on this array. The source option can be used with the schedule, retention, space, or snap options.<br><br>Optional.                                                                                                                              |
| space        | boolean | Displays (true) size and space consumption information for each volume associated with each specified protection group.<br><br>Optional.                                                                                                                                                              |
| target       | boolean | Lists (true) protection groups and snapshots replicated to this array. The target option can be used with the schedule, retention, space, or snap options.<br><br>Optional.                                                                                                                           |
| total        | boolean | Displays (true) the total space consumption for all protection groups. Must be used with the space parameter.<br><br>Optional.                                                                                                                                                                        |
| transfer     | boolean | Used with the snap parameter to display (true) replication data transfer statistics, including data transfer start time, data transfer end time, data transfer progress, and amount of logical/physical data transferred.<br><br>Optional.                                                            |

**Example 1: List all protection groups.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup
```

Response:

```
[
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg1",
    "source": "pure01",
    "targets": null,
    "volumes": [
      "v1"
    ]
  },
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg2",
    "source": "pure01",
    "targets": null,
    "volumes": [
      "v1"
    ]
  }
]
```

**Example 2: List all protection groups created on this array.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?source=true
```

Response:

```
[
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg1",
    "source": "pure01",
    "targets": null,
    "volumes": [
      "v1"
    ]
  },
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg2",
    "source": "pure01",
    "targets": null,
    "volumes": [
      "v1"
    ]
  }
]
```

**Example 3: List all protection groups and their schedules.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?schedule=true
```

Response:

```
[
  {
    "name": "pg1",
```

```

    "replicate_at": null,
    "replicate_blackout": null,
    "replicate_enabled": false,
    "replicate_frequency": 14400,
    "snap_at": null,
    "snap_enabled": false,
    "snap_frequency": 3600
  },
  {
    "name": "pg2",
    "replicate_at": null,
    "replicate_blackout": null,
    "replicate_enabled": false,
    "replicate_frequency": 14400,
    "snap_at": null,
    "snap_enabled": false,
    "snap_frequency": 3600
  }
]

```

**Example 4: List all protection groups and their retention policies.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?retention=true
```

Response:

```

[
  {
    "all_for": 86400,
    "days": 7,
    "name": "pg1",
    "per_day": 4,
    "target_all_for": 86400,
    "target_days": 7,
    "target_per_day": 4
  },
  {
    "all_for": 86400,
    "days": 7,
    "name": "pg2",
    "per_day": 4,
    "target_all_for": 86400,
    "target_days": 7,
    "target_per_day": 4
  }
]

```

**Example 5: List all protection groups including protection pgroups in the eradication pending state.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?pending=true
```

Response:

```

[
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg1",
    "source": "pure01",
    "targets": null,
    "time_remaining": null,
    "volumes": [
      "v1"
    ]
  },
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg2",
    "source": "pure01",
    "targets": null,
    "time_remaining": null,
    "volumes": [
      "v1"
    ]
  }
]

```

```
    "hgroups": null,
    ...
    "v3"
  ]
}
```

Example 6: List all protection groups in the eradication pending state.

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?pending_only=true
```

Response:

```
[
  {
    "hgroups": null,
    "hosts": null,
    "name": "pg3",
    "source": "pure01",
    "targets": null,
    "time_remaining": 86383,
    "volumes": [
      "v2",
      "v3"
    ]
  }
]
```

Example 7: List all protection groups and their space usage.

Request:

```
GET https://pure01.example.com/api/1.11/pgroup?space=true
```

Response:

```
[
  {
    "name": "pg1",
    "snapshots": 0
  },
  {
    "name": "pg2",
    "snapshots": 0
  }
]
```

6.2 GET pgroup/{pgroup}

Lists the attributes for the specified protection group or protection group snapshot.

If listing protection group snapshot attributes, the snap parameter must be specified.

Parameters

| Parameter    | Type    | Description                                                                                                                                                                                                                                                                                           |
|--------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| pending      | boolean | Includes (true) destroyed protection groups that are in the eradication pending state. Time remaining is displayed in seconds. The pending option can also be used with the schedule, retention, space, or snap options to include a list of pending protection groups or snapshots.<br><br>Optional. |
| pending_only | boolean | Used with the snap parameter to list (true) destroyed protection group snapshots that are in the eradication pending state. Time remaining is displayed in seconds.<br><br>Optional.                                                                                                                  |

|           |         |                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|-----------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| retention | boolean | Displays (true) the source/target retention policy.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                     |
| schedule  | boolean | Displays (true) the snapshot/replication schedule.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                      |
| snap      | boolean | If listing the attributes for a specified protection group, set snap to true to list all snapshots within the protection group. If listing the attributes for a specified protection group snapshot, always set snap to true.<br><br>Can be used with the space parameter to list space consumption for all snapshots.<br><br>Optional if listing attributes for a specified protection group. Required if listing attributes for a specified protection group snapshot. |
| space     | boolean | Displays (true) size and space consumption information for each volume associated with each specified protection group.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                 |
| total     | boolean | Used with the snap parameter to display (true) the total space consumption for all snapshots of this protection group. Must be used with the space parameter.<br><br>Optional.                                                                                                                                                                                                                                                                                           |
| transfer  | boolean | Used with the snap parameter to display (true) replication data transfer statistics, including data transfer start time, data transfer end time, data transfer progress, and amount of logical/physical data transferred.<br><br>Optional.                                                                                                                                                                                                                               |

**Example 1: List protection group pg1.**

Request:

GET https://pure01.example.com/api/1.11/pgroup/pg1

Response:

```
{
  "hgroups": null,
  "hosts": null,
  "name": "pg1",
  "source": "pure01",
  "targets": null,
  "volumes": [
    "v1"
  ]
}
```

**Example 2: List protection group pg3 even if it is in eradication pending state.**

Request:

GET https://pure01.example.com/api/1.11/pgroup/pg3?pending=true

Response:

```
{
  "hgroups": null,
  "hosts": null,
  "name": "pg3",
  "source": "pure01",
  "targets": null,
  "time_remaining": 86382,
  "volumes": [
    "v2",
    "v3"
  ]
}
```

**Example 3: List space usage for protection group pg1.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup/pg1?space=true
```

Response:

```
{
  "name": "pg1",
  "snapshots": 0
}
```

**Example 4: List schedule for protection group pg1.**

Request:

```
GET https://pure01.example.com/api/1.11/pgroup/pg1?schedule=true
```

Response:

```
{
  "name": "pg1",
  "replicate_at": null,
  "replicate_blackout": null,
  "replicate_enabled": false,
  "replicate_frequency": 14400,
  "snap_at": null,
  "snap_enabled": false,
  "snap_frequency": 3600
}
```

**6.3 POST pgroup**

Creates snapshots of one or more protection groups.

**Parameters**

| Parameter       | Type    | Description                                                                                                                                                                                                                                                                                                                           |
|-----------------|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| apply_retention | boolean | Applies the retention schedule settings of the protection group to the snapshot.<br><br>Optional.                                                                                                                                                                                                                                     |
| replicate       | boolean | Queues this snapshot for replication to all allowed target arrays. Purity will begin replicating data to each allowed target when all earlier replication sessions for the same protection group have been completed to that target, excluding those started with replicate_now. May not be used with replicate_now.<br><br>Optional. |
| replicate_now   | boolean | Replicates this snapshot immediately to all allowed target arrays. May not be used with replicate.<br><br>Optional.                                                                                                                                                                                                                   |
| snap            | boolean | Must be set to true to signify that a snapshot is being created.<br><br>Required.                                                                                                                                                                                                                                                     |
| source          | list    | Generates a snapshot for each of the protection groups specified.<br><br>Required.                                                                                                                                                                                                                                                    |
| suffix          | string  | Specifies a name suffix for the snapshot to be created.<br><br>Optional.                                                                                                                                                                                                                                                              |

**Example 1: Create a snapshot of protection group pg1.**

Request:

```
POST https://pure01.example.com/api/1.11/pgroup
{
  "snap": true,
  "source": [
    "pg1"
  ]
}
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:36Z",
    "name": "pg1.3",
    "source": "pg1"
  }
]
```

**Example 2: Create a snapshot of protection group pg1 with a custom suffix and apply pg1's retention policy to it.**

Request:

```
POST https://pure01.example.com/api/1.11/pgroup
{
  "apply_retention": true,
  "snap": true,
  "source": [
    "pg1"
  ],
  "suffix": "crackle"
}
```

Response:

```
[
  {
    "created": "2017-03-13T19:42:36Z",
    "name": "pg1.crackle",
    "source": "pg1"
  }
]
```

**6.4 POST pgroup/{pgroup}**

Creates a protection group with the specified name or copies a protection group.

When copying a protection group, the destination protection group is created if it did not exist previously.

**Parameters**

| Parameter  | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
|------------|---------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hgrouplist | list    | List of one or more host groups to be included in the new protection group.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                   |
| hostlist   | list    | List of one or more hosts to be included in the new protection group.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                         |
| overwrite  | boolean | When copying a protection group, overwrite (true) volumes in the destination protection group that have the same name as the volumes in the source protection group. Without the overwrite=true parameter, the copy command fails if any volume name collisions are found. With the overwrite=true parameter, both the source and destination protection groups must contain exactly the same volumes (volume names), otherwise the entire copy command fails. |

|            |        |                                                                         |
|------------|--------|-------------------------------------------------------------------------|
|            |        | Optional.                                                               |
| source     | string | The source pgroup or pgroup snapshot to copy from.                      |
|            |        | Optional.                                                               |
| targetlist | list   | List of one or more targets to be included in the new protection group. |
|            |        | Optional.                                                               |
| vollist    | list   | List of one or more volumes to be included in the new protection group. |
|            |        | Optional.                                                               |

**Example 1: Create protection group pg4.**

Request:

```
POST https://pure01.example.com/api/1.11/pgroup/pg4
```

Response:

```
{
  "hgroups": null,
  "hosts": null,
  "name": "pg4",
  "source": "pure01",
  "targets": null,
  "volumes": null
}
```

**Example 2: Create protection group pg5 with host h1.**

Request:

```
POST https://pure01.example.com/api/1.11/pgroup/pg5
{
  "hostlist": [
    "h1"
  ]
}
```

Response:

```
{
  "hgroups": null,
  "hosts": [
    "h1"
  ],
  "name": "pg5",
  "source": "pure01",
  "targets": null,
  "volumes": null
}
```

**6.5 PUT pgroup/{pgroup}**

Modifies a protection group, its snapshot/replication schedule or its retention policy.

At least one parameter must be specified.

**Parameters**

| Parameter | Type   | Description                                                             |
|-----------|--------|-------------------------------------------------------------------------|
| action    | string | If set to "recover", recovers a destroyed protection group or snapshot. |
|           |        | Optional.                                                               |

|                    |         |                                                                                                                                                                                          |
|--------------------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| addhgrouplist      | list    | Adds a list of host groups to the existing list.<br><br>Optional.                                                                                                                        |
| addhostlist        | list    | Adds a list of hosts to the existing list.<br><br>Optional.                                                                                                                              |
| addtargetlist      | list    | Adds a list of target arrays to the existing list.<br><br>Optional.                                                                                                                      |
| addvollist         | list    | Adds a list of volumes to the existing list.<br><br>Optional.                                                                                                                            |
| all_for            | number  | Modifies the retention policy of the protection group. Specifies the length of time to keep the snapshots on the source array before they are eradicated.<br><br>Optional.               |
| allowed            | boolean | Allows (true) or disallows (false) a protection group from being replicated.<br><br>Optional.                                                                                            |
| days               | number  | Modifies the retention policy of the protection group. Specifies the number of days to keep the per_day snapshots beyond the all_for period before they are eradicated.<br><br>Optional. |
| hgrouplist         | list    | Replaces the list of member host groups.<br><br>Optional.                                                                                                                                |
| hostlist           | list    | Replaces the list of member hosts.<br><br>Optional.                                                                                                                                      |
| name               | string  | Renames a protection group.<br><br>Optional.                                                                                                                                             |
| per_day            | number  | Modifies the retention policy of the protection group. Specifies the number of per_day snapshots to keep beyond the all_for period.<br><br>Optional.                                     |
| remhgrouplist      | list    | Removes a list of host groups from the existing list.<br><br>Optional.                                                                                                                   |
| remhostlist        | list    | Removes a list of hosts from the existing list.<br><br>Optional.                                                                                                                         |
| remtargetlist      | list    | Removes a list of target arrays from the existing list.<br><br>Optional.                                                                                                                 |
| remvollist         | list    | Removes a list of volumes from the existing list.<br><br>Optional.                                                                                                                       |
| replicate_at       | number  | Modifies the replication schedule of the protection group. Specifies the preferred time, on the hour, at which to replicate the snapshots.<br><br>Optional.                              |
| replicate_blackout | object  | Modifies the replication schedule of the protection group. Specifies the range of time at which to suspend replication. See the example for the dictionary format.<br><br>Optional.      |

|                     |         |                                                                                                                                                                                                                   |
|---------------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| replicate_enabled   | boolean | Used to enable (true) or disable (false) the protection group replication schedule.<br><br>Optional.                                                                                                              |
| replicate_frequency | number  | Modifies the replication schedule of the protection group. Specifies the replication frequency.<br><br>Optional.                                                                                                  |
| snap_at             | number  | Modifies the snapshot schedule of the protection group. Specifies the preferred time, on the hour, at which to generate the snapshot.<br><br>Optional.                                                            |
| snap_enabled        | boolean | Used to enable (true) or disable (false) the protection group snapshot schedule.<br><br>Optional.                                                                                                                 |
| snap_frequency      | number  | Modifies the snapshot schedule of the protection group. Specifies the snapshot frequency.<br><br>Optional.                                                                                                        |
| target_all_for      | number  | Modifies the retention policy of the protection group. Specifies the length of time to keep the replicated snapshots on the target arrays.<br><br>Optional.                                                       |
| target_days         | number  | Modifies the retention policy of the protection group. Specifies the number of days to keep the target_per_day replicated snapshots beyond the target_all_for period before they are eradicated.<br><br>Optional. |
| target_per_day      | number  | Modifies the retention policy of the protection group. Specifies the number of per_day replicated snapshots to keep beyond the target_all_for period.<br><br>Optional.                                            |
| targetlist          | list    | Replaces the list of member target arrays.<br><br>Optional.                                                                                                                                                       |
| vollist             | list    | Replaces the list of member volumes.<br><br>Optional.                                                                                                                                                             |

**Example 1: Rename protection group**

Request:

```
PUT https://pure01.example.com/api/1.11/pgroup/pg2
{
  "name": "pg6"
}
```

Response:

```
{
  "name": "pg6"
}
```

**Example 2: Set host members**

Request:

```
PUT https://pure01.example.com/api/1.11/pgroup/pg4
{
  "hostlist": [
    "h3"
  ]
}
```

Response:

```
{
  "hgroups": null,
  "hosts": [
    "h3"
  ],
  "name": "pg4",
  "source": "pure01",
  "targets": null,
  "volumes": null
}
```

**Example 3: Enables the replication schedule for pg4**

Request:

```
PUT https://pure01.example.com/api/1.11/pgroup/pg4
{
  "replicate_enabled": true
}
```

Response:

```
{
  "name": "pg4",
  "replicate_at": null,
  "replicate_blackout": null,
  "replicate_enabled": true,
  "replicate_frequency": 14400,
  "snap_at": null,
  "snap_enabled": false,
  "snap_frequency": 3600
}
```

**Example 4: Sets a replication blackout window from 2am to 4am (in seconds) for pg4**

Request:

```
PUT https://pure01.example.com/api/1.11/pgroup/pg4
{
  "replicate_blackout": {
    "end": 14400,
    "start": 7200
  }
}
```

Response:

```
{
  "name": "pg4",
  "replicate_at": null,
  "replicate_blackout": [
    {
      "end": 14400,
      "start": 7200
    }
  ],
  "replicate_enabled": true,
  "replicate_frequency": 14400,
  "snap_at": null,
  "snap_enabled": false,
  "snap_frequency": 3600
}
```

**Example 5: Sets a retention policy to retain all snapshots for 3 days (in minutes), and keep 12 snapshots per day after the all\_for period ends**

Request:

```
PUT https://pure01.example.com/api/1.11/pgroup/pg4
{
  "all_for": 4320,
  "per_day": 12
}
```

Response:

```
{
  "all_for": 4320,
  "days": 7,
  "name": "pg4",
  "per_day": 12,
  "target_all_for": 86400,
  "target_days": 7,
  "target_per_day": 4
}
```

## 6.6 DELETE pgroup/{pgroup}

Destroys or eradicates the specified protection group or protection group snapshot.

### Parameters

| Parameter | Type    | Description                                                                                                                                                                                                |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| eradicate | boolean | Eradicates the destroyed protection group or protection group snapshot. If destroying or eradicating a protection group, its protection group snapshots are also destroyed or eradicated.<br><br>Optional. |

### Example 1: Destroys protection group pg5

Request:

```
DELETE https://pure01.example.com/api/1.11/pgroup/pg5
```

Response:

```
{
  "name": "pg5"
}
```

### Example 2: Eradicates protection group pg5

Request:

```
DELETE https://pure01.example.com/api/1.11/pgroup/pg5
{
  "eradicate": true
}
```

Response:

```
{
  "name": "pg5"
}
```

## 7. Connection Ports

View array host connection port attributes.

### 7.1 GET port

Lists array ports and the worldwide names assigned to each port.

### Parameters

|  |  |  |
|--|--|--|
|  |  |  |
|--|--|--|

| Parameter  | Type    | Description                                                                                                                                                                                    |
|------------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| initiators | boolean | Displays host worldwide names (both those discovered by Purity and those assigned by administrators) and the array ports (targets) on which they are eligible to communicate.<br><br>Optional. |

**Example 1: List all ports**

Request:

```
GET https://pure01.example.com/api/1.11/port
```

Response:

```
[
  {
    "failover": null,
    "iqn": null,
    "name": "CT0.FC0",
    "portal": null,
    "wwn": "5001500150015080"
  },
  {
    "failover": null,
    "iqn": null,
    "name": "CT0.FC1",
    "portal": null,
    "wwn": "5001500150015081"
  },
  {
    "failover": null,
    "iqn": null,
    "name": "CT0.FC2",
    "portal": null,
    "wwn": "5001500150015090"
  },
  {
    "failover": null,
    "iqn": null,
    "name": "CT0.FC3",
    "portal": null,
    "wwn": "5001500150015091"
  }
]
```

**Example 2: List all initiator ports**

Request:

```
GET https://pure01.example.com/api/1.11/port?initiators=true
```

Response:

```
[
  {
    "failover": null,
    "iqn": null,
    "portal": null,
    "target": null,
    "target_iqn": null,
    "target_portal": null,
    "target_wwn": null,
    "wwn": "0000111122223333"
  },
  {
    "failover": null,
    "iqn": null,
    "portal": null,
    "target": "CT0.FC1",
    "target_iqn": null,
    "target_portal": null,
    "target_wwn": "00000000000000001",
    "wwn": "0003000300030003"
  },
  {
    "failover": null,
    "iqn": null,
    "portal": null,

```

```
...
  "target_wwn": "0000000000000000",
  "wwn": "0009000900090009"
}
]
```

## 8. Alerts and Messages

View a list of email addresses designated to receive Purity alerts, test the alert feature, enable or disable alert notifications, designate email addresses to receive Purity alerts, and remove email addresses from the list of designated alert recipients. View a list of alert events, audit records, and user login sessions. Flag alert and audit messages.

### 8.1 GET alert

Lists email recipients that are designated to receive Purity alert messages.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

#### Example 1: List all alert recipients

Request:

```
GET https://pure01.example.com/api/1.11/alert
```

Response:

```
[
  {
    "enabled": false,
    "name": "flasharray-alerts@purestorage.com"
  }
]
```

### 8.2 GET alert/{address}

Lists information about the specified email recipient.

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

#### Example 1: List a single alert recipient

Request:

```
GET https://pure01.example.com/api/1.11/alert/flasharray-alerts@purestorage.com
```

Response:

```
{
  "enabled": false,
  "name": "flasharray-alerts@purestorage.com"
}
```

### 8.3 POST alert/{address}

Designates any valid email address to receive Purity alert messages.

Up to 20 addresses can be designated in an array (19 in addition to the built-in `flasharray-alerts@purestorage.com` address.)

#### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

#### Example 1: Add a new alert recipient

Request:

```
POST https://pure01.example.com/api/1.11/alert/admin@example.com
```

Response:

```
{
  "enabled": true,
  "name": "admin@example.com"
}
```

## 8.4 PUT alert

Tests the ability of the array to send alert messages to all of the designated email addresses.

#### Parameters

| Parameter | Type   | Description                                                                                                                                                                                                                     |
|-----------|--------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string | Set the parameter to "test" to test the ability of the array to send alert messages to all of the designated email addresses. Verification of successful test message transmission is done at the destination.<br><br>Required. |

## 8.5 PUT alert/{address}

Tests, enables, and disables the transmission of alert messages to the specified email address.

At least one parameter must be specified.

#### Parameters

| Parameter | Type    | Description                                                                                                                                                                                                                              |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action    | string  | Set the parameter to "test" to test the ability of the array to send alert messages to the specified email address, designated or not. Verification of successful test message transmission is done at the destination.<br><br>Optional. |
| enabled   | boolean | Enables (true) or disables (false) the transmission of alert messages to the specified email address.<br><br>Optional.                                                                                                                   |

#### Example 1: Disable a single alert recipient

Request:

```
PUT https://pure01.example.com/api/1.11/alert/admin@example.com
{
  "enabled": false
}
```

```
}
```

Response:

```
{
  "enabled": false,
  "name": "admin@example.com"
}
```

## 8.6 DELETE alert/{address}

Deletes an email address from the list of addresses designated to receive Purity alert messages. You cannot delete the built-in flasharray-alerts@purestorage.com address.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: Delete a single alert recipient

Request:

```
DELETE https://pure01.example.com/api/1.11/alert/admin@example.com
```

Response:

```
{
  "name": "admin@example.com"
}
```

## 8.7 GET message

Lists alert events, audit records, and user login sessions.

### Parameters

| Parameter | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                             |
|-----------|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| audit     | boolean | Lists audit records instead of alerts (default). May not be used with login or open.<br>Optional.                                                                                                                                                                                                                                                                                                       |
| flagged   | boolean | Lists flagged messages only. The array automatically flags warnings and critical alerts.<br>Optional.                                                                                                                                                                                                                                                                                                   |
| login     | boolean | Lists user session logs instead of alerts (default). May not be used with audit or open.<br>Optional.                                                                                                                                                                                                                                                                                                   |
| open      | boolean | Lists open messages. May not be used with audit or login.<br>Optional.                                                                                                                                                                                                                                                                                                                                  |
| recent    | boolean | Lists recent messages. An audit record is considered recent if it relates to a command issued within the past 24 hours. An alert is considered recent if the situation that triggered it is unresolved, or has only been resolved within the past 24 hours. A user session log event is considered recent if the login, logout, or authentication event occurred within the past 24 hours.<br>Optional. |
| user      | string  | When audit is set to true, user can be used to list audit records for a specific user. When login is set to                                                                                                                                                                                                                                                                                             |

true, user can be used to list user session logs for a specific user.

Optional.

Example 1: List all alert messages

Request:

```
GET https://pure01.example.com/api/1.11/message
```

Response:

```
[]
```

Example 2: List all audit trail messages

Request:

```
GET https://pure01.example.com/api/1.11/message?audit=true
```

Response:

```
[
  {
    "component_name": null,
    "component_type": "purearray",
    "details": "--senderdomain example.com",
    "event": "setattr",
    "id": 2,
    "opened": "2017-03-13T19:39:38Z",
    "user": "root"
  },
  {
    "component_name": null,
    "component_type": "puredns",
    "details": "--domain example.com --nameservers 192.168.0.1,192.168.1.1",
    "event": "setattr",
    "id": 69,
    "opened": "2017-03-13T19:40:09Z",
    "user": "root"
  },
  {
    "component_name": null,
    "component_type": "purecloudcert",
    "details": "",
    "event": "add",
    "id": 578,
    "opened": "2017-03-13T19:42:37Z",
    "user": "os76"
  },
  ...
]
```

8.8 PUT message/{id}

Flags or unflags a message.

Parameters

| Parameter | Type    | Description                                                                                                                                                |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------|
| flagged   | boolean | Flags (true) or unflags (false) a message. If set to true, flags the message with the specified ID. If set to false, unflags the message.<br><br>Required. |

9. SNMP Manager Connections

View and set SNMP manager and trap message attributes.

## 9.1 GET snmp

Lists designated SNMP managers and their communication and security attributes.

### Parameters

| Parameter | Type    | Description                                                                                                                    |
|-----------|---------|--------------------------------------------------------------------------------------------------------------------------------|
| engine_id | boolean | SNMP v3 only. If set to <code>true</code> , displays the SNMP v3 engine ID generated by Purity for the array.<br><br>Optional. |

### Example 1: List all SNMP managers

Request:

```
GET https://pure01.example.com/api/1.11/snmp
```

Response:

```
[
  {
    "auth_passphrase": null,
    "auth_protocol": null,
    "community": null,
    "host": "localhost",
    "name": "localhost",
    "privacy_passphrase": null,
    "privacy_protocol": null,
    "user": null,
    "version": "v2c"
  }
]
```

### Example 2: List SNMP v3 engine ID

Request:

```
GET https://pure01.example.com/api/1.11/snmp?engine_id=true
```

Response:

```
{
  "engine_id": "80009e2205c288160732840fd76f9a76"
}
```

## 9.2 GET snmp/{manager}

Lists communication and security attributes for the specified SNMP manager.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 9.3 POST snmp/{manager}

Creates a Purity SNMP manager object that identifies a host (SNMP manager) and specifies the protocol attributes for communicating with it.

Once a manager object is created, the transmission of SNMP traps is immediately enabled.

### Parameters

| Parameter          | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|--------------------|--------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| auth_passphrase    | string | SNMP v3 only. Passphrase used by Purity to authenticate the array with the specified managers. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and - (hyphen)}.<br><br>Required if the auth-protocol value is set.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| auth_protocol      | string | SNMP v3 only. Hash algorithm used to validate the authentication passphrase. Valid values are MD5 or SHA.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| community          | string | SNMP v2c only. Manager community ID under which Purity is to communicate with the specified managers. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and - (hyphen)}.<br><br>Required if the version parameter is set to v2c.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| host               | string | DNS hostname or IP address of a computer that hosts an SNMP manager to which Purity is to send trap messages when it generates alerts.<br><br>If specifying an IP address, enter the IPv4 or IPv6 address.<br><br>For IPv4, specify the IP address in the form ddd . ddd . ddd . ddd, where ddd is a number ranging from 0 to 255 representing a group of 8 bits. If a port number is also specified, append it to the end of the address in the format ddd . ddd . ddd . ddd : PORT, where PORT represents the port number.<br><br>For IPv6, specify the IP address in the form xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx, where xxxx is a hexadecimal number representing a group of 16 bits. Consecutive fields of zeros can be shortened by replacing the zeros with a double colon ( : : ). If a port number is also specified, enclose the entire address in square brackets ( [ ] ) and append the port number to the end of the address. For example, [ xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx ] : PORT, where PORT represents the port number.<br><br>Required. |
| privacy_passphrase | string | SNMP v3 only. Passphrase used to encrypt SNMP messages. The value must be between 8 and 63 non-space ASCII characters in length.<br><br>Required if the privacy-protocol value is set.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| privacy_protocol   | string | SNMP v3 only. Encryption protocol for SNMP messages. Valid values are AES or DES.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| user               | string | SNMP v3 only. User ID recognized by the specified SNMP managers which Purity is to use in communications with them. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and - (hyphen)}.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| version            | string | Version of the SNMP protocol to be used by Purity in communications with the specified manager(s). The version value is case sensitive. Valid values are v2c (default) and v3.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |

## 9.4 PUT snmp/{manager}

Changes name or the protocol attributes of the specified SNMP manager.

At least one parameter must be specified.

### Parameters

| Parameter | Type   | Description                                                                    |
|-----------|--------|--------------------------------------------------------------------------------|
| action    | string | Set the parameter to "test" to send a test trap to the specified SNMP manager. |

|                    |        |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|--------------------|--------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| auth_passphrase    | string | SNMP v3 only. Passphrase used by Purity to authenticate the array with the specified managers. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and - (hyphen)}.                                                                                                                                                                                                                                                                             |
|                    |        | Required if the auth_protocol value is set.                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| auth_protocol      | string | SNMP v3 only. Hash algorithm used to validate the authentication passphrase. Valid values are MD5 or SHA.                                                                                                                                                                                                                                                                                                                                                                                                  |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| community          | string | SNMP v2c only. Manager community ID under which Purity is to communicate with the specified managers. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and - (hyphen)}.                                                                                                                                                                                                                                                                      |
|                    |        | Required if the version parameter is set to v2c.                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| host               | string | DNS hostname or IP address of a computer that hosts an SNMP manager to which Purity is to send trap messages when it generates alerts.                                                                                                                                                                                                                                                                                                                                                                     |
|                    |        | If specifying an IP address, enter the IPv4 or IPv6 address.                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|                    |        | For IPv4, specify the IP address in the form ddd.ddd.ddd.ddd, where ddd is a number ranging from 0 to 255 representing a group of 8 bits. If a port number is also specified, append it to the end of the address in the format ddd.ddd.ddd.ddd:PORT, where PORT represents the port number.                                                                                                                                                                                                               |
|                    |        | For IPv6, specify the IP address in the form xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx, where xxxx is a hexadecimal number representing a group of 16 bits. Consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :). If a port number is also specified, enclose the entire address in square brackets ([ ]) and append the port number to the end of the address. For example, [xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx]:PORT, where PORT represents the port number. |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| name               | string | New name of the SNMP manager. SNMP manager names are used in Purity administrative commands, and have no external significance. Changing the name of the SNMP manager does not change the protocol and security attributes of the manager object.                                                                                                                                                                                                                                                          |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| privacy_passphrase | string | SNMP v3 only. Passphrase used to encrypt SNMP messages. The value must be between 8 and 63 non-space ASCII characters in length.                                                                                                                                                                                                                                                                                                                                                                           |
|                    |        | Required if the privacy_protocol value is set.                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| privacy_protocol   | string | SNMP v3 only. Encryption protocol for SNMP messages. Valid values are AES or DES.                                                                                                                                                                                                                                                                                                                                                                                                                          |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| user               | string | SNMP v3 only. User ID recognized by the specified SNMP managers which Purity is to use in communications with them. The value must be between 1 and 32 characters in length and from the set {[A-Z], [a-z], [0-9], _ (underscore), and -(hyphen)}.                                                                                                                                                                                                                                                         |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| version            | string | Version of the SNMP protocol to be used by Purity in communications with the specified manager(s). The version value is case sensitive. Valid values are v2c (default) and v3.                                                                                                                                                                                                                                                                                                                             |
|                    |        | Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

## 9.5 DELETE snmp/{manager}

Stops communication with the specified managers and deletes the SNMP manager object.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
|-----------|------|-------------|

|      |     |     |
|------|-----|-----|
| None | n/a | n/a |
|------|-----|-----|

## 10. SSL Certificate

View and manage SSL certificates.

### 10.1 GET cert

Lists certificate attributes or exports certificates.

If the request does not include parameters, the REST API call returns the attributes of the certificate. Include the `certificate` or `intermediate_certificate` parameter to export the respective certificate.

#### Parameters

| Parameter                | Type    | Description                                                                                  |
|--------------------------|---------|----------------------------------------------------------------------------------------------|
| certificate              | boolean | If set to <code>true</code> , exports the current certificate.<br><br>Optional.              |
| intermediate_certificate | boolean | If set to <code>true</code> , exports the current intermediate certificate.<br><br>Optional. |

#### Example 1: List the attributes of the current certificate

Request:

```
GET https://pure01.example.com/api/1.11/cert
```

Response:

```
{
  "country": "US",
  "email": null,
  "issued_by": "db.purestorage.com",
  "issued_to": "db.purestorage.com",
  "key_size": 2048,
  "locality": "Mountain View",
  "organization": "Pure Storage Inc.",
  "organizational_unit": null,
  "state": "CA",
  "status": "self-signed",
  "valid_from": "2017-03-13T19:42:19Z",
  "valid_to": "2027-03-11T19:42:19Z"
}
```

#### Example 2: Export the current certificate

Request:

```
GET https://pure01.example.com/api/1.11/cert?certificate=true
```

Response:

```
{
  "certificate": "-----BEGIN CERTIFICATE-----
\nMIIDUjCCAjoCCQCQ00T/ItDvjRDANBgkqhkiG9w0BAQsFADBrMRYwFAYDVQQHDA1Nb3VudGFpbiBwawV3MQswCQYDVQQGEwJVUzELMAkGA1UE
CAwCQ0ExGzAZBgNVBAMM\nEmRiLnB1cmVzdG9yYWdlLmNvbTEaMBGGA1UECgwRUHVyZSBTdG9yYWdlIEluYy4w\nnHhcNMTcwMzEzMTk0MjE5WWhcN
MjcwMzE5MTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcNMTk0MjE5WWhcN
cmVzdG9yYWdlLmNvbTEaMBGGA1UECgwRUHVyZSBTdG9yYWdlIEluYy4wggEi\nnMA0GCsGSIb3DQEBAQUAA4IBDwAwggEKAoIBAQC8mpw5nFQFBj
+ui89i1YBE7o1T\nnPXGQy6Sj9HlRiWTTQXGAYEedccBA+u+CoUyF0+D2u/Q3l2SiF05s88Le1ubK0s2v\nnA3exVqysZ+2JzTf/nvD2dfxer1QtM
2u3AwvNE2WD+GtSY+9AVEH7T/AmaitoiPF\nnfksHZp/Q0E2Nhp1SxD+UegCYE/mxJ+v06DPTcVvSbyvf9+Ke02qKPNJCDi+h7rLH\nnb+fnpneaK2
vvYSF4nA03v7d1sFLMnS9lXPrXtz0V/+602+ew0Ias/Y7RVsG6VCKt\nnyxBkq3PTU9ki7glyXAzkwSdE2SNw/nbbQJd2PfKLYBhk++nt127H8HoE
/r11AgMB\nnAAEwDQYJKoZIhvcNAQELBQADggEBACxPte6zeJMp/paR0nHoXIDgARaj0uHG009X\nnr+1Q25IEIqD/blwyabTQE/98Asj16Kve1/hx
59+f9ovhnrKAgRkupl8SmReM8iWk\nnSwSkXV8ynLks4FzkbozR41rarqJBMx1uhZSq+1azTS9+IJogV0v39x7mpzzOc3A4\nn55iP5Ud9KJTjYZ1X
Djw729FGz7mHS1yGrCYKepYcCu0A5w9eRyLtmYFCHqQRYunx\nnZvna67Mq9s0hte7gUvKaweqadbg2hzL+hKKS0McfrPaSldLGK1qv2kMBS5lYMY
iR\nNgY1LWehCXmChb8XX4FS9L9gF87UY4DW+NcixvuywAGU1w6SjE18=\n-----END CERTIFICATE-----\n"
```

}

## 10.2 GET cert/certificate\_signing\_request

Constructs a certificate signing request (CSR) for signing by a certificate authority (CA).

### Parameters

| Parameter           | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                     |
|---------------------|--------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| common_name         | string | Sets the common name of the CSR. The common name must be the fully qualified domain name of the current array. For example, for https://purearray.example.com, the common name must be purearray.example.com or *.example.com for a wildcard certificate. It can also be the management IP address of the array or the short name of the current array. It can't have more than 64 characters.<br><br>Optional. |
| country             | string | Sets the country name of the CSR. The country name represents the two-letter ISO code for the country where your organization is located.<br><br>Optional.                                                                                                                                                                                                                                                      |
| email               | string | Sets the email address used to contact your organization.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                      |
| locality            | string | Sets the name of the city where your organization is located.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                  |
| organization        | string | Sets the name of your organization. Enter the full and exact legal name of your organization. The organization name should not be abbreviated and should include suffixes such as Inc, Corp, or LLC. For example, 'Pure Storage, Inc.'<br><br>Optional.                                                                                                                                                         |
| organizational_unit | string | Sets the name of the department within your organization that you want to appear in the certificate.<br><br>Optional.                                                                                                                                                                                                                                                                                           |
| state               | string | Sets the name of the state or province where your organization is located.<br><br>Optional.                                                                                                                                                                                                                                                                                                                     |

### Example 1: Construct a CSR with the current certificate attributes

Request:

```
GET https://pure01.example.com/api/1.11/cert/certificate_signing_request
```

Response:

```
{
  "certificate_signing_request": "-----BEGIN CERTIFICATE REQUEST-----
\nMIICzjCCABYCAQAwgYgxFjAUBgNVBACMDU1vdW50YWluIFZpZxcxZzAJBgNVBAYT\nnA1VMTQswCQYDVQIDAJDQTEbMBkGA1UECwwSUHVyZSBT
dG9yYwd1LCBjbmuMRsw\ngQYDVQDDBJkYi5wdXJlc3RvcnFnZS5jb20xGjAYBgNVBAoMEVB1cmUgU3RvcnFn\nnZSBjbmuMIIBiJANBgkqhkiG
9w0BAQEFAAOCAQ8AMIIBCgKCAQEAJqVuZxUBQSF\nrovPYtWAR06NUz1xkMuko/R5UY1k7UFxgMhHg3HAQPrvggFMhTvg9rv0N5dkohd0\nnbPPC
3tbmyjrNrwN3sVasrM/tic03/57w9nX68RK9ULTNrtwMLzRNlg/hrUmPvQFR\nnB+0/wdGoraIjxX5LB2af0NBNjYadUsQ/1HoAmBP5sSfr90gz03
Fb0m8r3/fintNg\nnijzSQg4v0e65R2/n56Z3mitr72EheJwDt7+3dbBSzJ0vZVz617c9Ff/utNvnltCG\n\nkv200VbBulQircsQZKtz01PZiu4Jcl
wM5MErNKjVv5220CXdj35C2AYZPvp7ddu\n\nx/B6BP64tQIDAQABoAAwDQYJKoZIhvcNAQELBQADggEBAFNgfQr1SMBFESjxMlqZ\n\nPEDKMPDkBO
0c2MDJ3Wu0V0EF9Pkr2KnUrEv9sUrXeLv/ZIjrTZ6EL2bw8L8AoUj\n\nndf/bUKh7kELslfBjzpQNMhPgMf0+mtSQ2rDth/pHEuD+e91CgZpmfWUk
nL2ncDq1\n\nl9QbXbPUTtmPWPPv5KI54HrwpmXf3Swg6J2X2bjeq3Dw79bPneoHP8c90057CsRU\n\nn02WE+8qtpJfh0bk6Xk9rqlGGbVT02LLD+yWa
IWkmh+mFcPCgoF9MGFWIWMUeSPdn\ngG8rBpnf2ewS5tUXowLi1Cv5uCBCd1MRLeGvaf1WB/t7bpqx7NBA1KZU3Tjt4uPr\n\nnut4=\n\n-----END
CERTIFICATE REQUEST-----\n"
}
```

### Example 2: Construct a CSR with the current certificate attributes, but change the common name to db.example.com

## Request:

```
GET https://pure01.example.com/api/1.11/cert/certificate_signing_request?common_name=db.example.com
```

## Response:

```
{
  "certificate_signing_request": "-----BEGIN CERTIFICATE REQUEST-----
\nMIICyJCABICAQAwgYQxFjAUBgNVBAcMDU1vdW50YWluIFZpZxcxCzAJBgNVBAYT\nAlVTMQswCQYDVQIDAJDQTEbMBkGA1UECwwSUHVyZSBT
dG9yYwdlLCBjb2MwMRcw\nFQYDVQDDA5kYi5leGFtcGxlLmNvbTEaMBGGA1UECgwRUHVyZSBTdG9yYwdlIElu\nnYy4wggEiMA0GCSqGSIb3DQEB
AQUAA4IBDwAwggEKAoIBAQC8mpw5nFQFBJ+ui89i\nn1YBE7o1TPXGQy6Sj9HlRiWtTQXGAYEedccBA+u+CoUyF0+D2u/Q3l2SiF05s88Le\nn1ubK
0S2vA3exVqysz+2JzTf/nVD2dfrxer1QtM2u3AwvNE2WD+GtSY+9AVEH7T/A\nnMaito1PFFksHZp/Q0E2Nhp1SxD+UegCYE/mxJ+v06DPTcVvSby
vf9+Ke02qKPNJC\nDi+h7r1Hb+fnpneaK2vvYSF4nA03v7d1sFLMnS9lXPrXtz0V/+602+ew0IaS/Y7R\nnVsG6VCKtyxBkq3PTU9ki7glyXAzkWS
dE2SNW/nbbQJd2PfkLYBhk++nt127H8HoE\n/ri1AgMBAAGgADANBgkqhkiG9w0BAQsFAA0CAQEAJzxChw1a7CRM0yrB17Y+TScE\n\nabwhhR+ioP
cjW+/okBtghP29bhqjmSeQi/gXYI9jncMZoSPWTLr3GtJddqFXKAhIP\nnd4Dl9M0wBdVaFelUGDUJvFE7qKPLAuPV08KZIuckbZXw0wa5YVLrPMQL
XVAiichD\nnUfwIAAQL5097N5XxEUTAFs9mq0a3mmJxYIrpUwd1is+ybb+Im9Le24NPq5i2EiJo\nn6C00g6hef3IMi0bzyILw/tD40EbRgyI1uh3c
swZBoFqvMkdVJ+Cn9cxuPly+9Gu1\nnpE8zCFJ/U51fNFB0oXuewSpNPkMbt9Zmnws57g2/UYZ75Sb3a/vYpsVM7YxxcA==\n-----END
CERTIFICATE REQUEST-----\n"
}
```

### 10.3 PUT cert

Creates a self-signed certificate or imports a certificate signed by a certificate authority (CA).

Creating a self-signed certificate or importing a certificate replaces the existing certificate. Either the `certificate` or `self-signed` parameter must be specified.

#### Parameters

| Parameter                | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|--------------------------|--------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| certificate              | string | Imports a certificate signed by a certificate authority.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                        |
| common_name              | string | Used with the <code>self-signed</code> parameter to specify the common name. The common name represents the qualified domain name of the current array. For example, for <code>https://purearray.example.com</code> , the common name must be <code>purearray.example.com</code> or <code>*.example.com</code> for a wildcard certificate. It can also be the management IP address of the array or the short name of the current array. It can't have more than 64 characters.<br><br>Optional. |
| country                  | string | Used with the <code>self-signed</code> parameter to specify the country name. The country name represents the two-letter ISO code for the country where your organization is located.<br><br>Optional.                                                                                                                                                                                                                                                                                           |
| days                     | int    | Used with the <code>self-signed</code> parameter to specify the number of valid days for the self-signed certificate being generated.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                           |
| email                    | string | Used with the <code>self-signed</code> parameter to specify the email address used to contact your organization.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                |
| intermediate_certificate | string | Used with the <code>certificate</code> parameter to specify the intermediate certificate to import.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                             |
| key                      | string | Used with the <code>certificate</code> parameter to specify the private key to import.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                          |
| key-size                 | int    | Used with the <code>new_key</code> parameter to specify the key size in bits. Valid values are 512, 1024, 2048 (default) or 4096. A key size smaller than 2048 is considered insecure.<br><br>Optional.                                                                                                                                                                                                                                                                                          |

|                     |         |                                                                                                                                                                                                                                                              |
|---------------------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| locality            | string  | Used with the self-signed parameter to specify the city where your organization is located.<br><br>Optional.                                                                                                                                                 |
| new_key             | boolean | Used with the self-signed parameter to create a new key when creating the self-signed certificate. If a new private key is not generated, the certificate uses the existing private key.<br><br>Optional.                                                    |
| organization        | string  | Used with the self-signed parameter to specify the full and exact legal name of your organization. The organization name should not be abbreviated and should include suffixes such as Inc, Corp, or LLC. For example, 'Pure Storage, Inc.'<br><br>Optional. |
| organizational_unit | string  | Used with the self-signed parameter to specify the department within your organization that you want to appear in the certificate.<br><br>Optional.                                                                                                          |
| passphrase          | string  | Used with the key parameter to decrypt the private key.<br><br>Optional.                                                                                                                                                                                     |
| self_signed         | boolean | Generates a self-signed certificate.<br><br>self_signed or certificate must be set.<br><br>Optional.                                                                                                                                                         |
| state               | string  | Used with the self-signed parameter to specify the state or province where your organization is located.<br><br>Optional.                                                                                                                                    |

**Example 1: Generate a self-signed certificate with the current certificate attributes**

Request:

```
PUT https://pure01.example.com/api/1.11/cert
{
  "self_signed": true
}
```

Response:

```
{
  "country": "US",
  "email": null,
  "issued_by": "db.purestorage.com",
  "issued_to": "db.purestorage.com",
  "key_size": 2048,
  "locality": "Mountain View",
  "organization": "Pure Storage Inc.",
  "organizational_unit": "Pure Storage, Inc.",
  "state": "CA",
  "status": "self-signed",
  "valid_from": "2017-03-13T19:42:38Z",
  "valid_to": "2027-03-11T19:42:38Z"
}
```

**Example 2: Generate a self-signed certificate with the current certificate attributes, but change the state to FL and the common name to db.example.com**

Request:

```
PUT https://pure01.example.com/api/1.11/cert
{
  "common_name": "db.example.com",
  "self_signed": true,
  "state": "FL"
}
```

Response:

```
{
  "country": "US",
  "email": null,
  "issued_by": "db.example.com",
  "issued_to": "db.example.com",
  "key_size": 2048,
  "locality": "Mountain View",
  "organization": "Pure Storage Inc.",
  "organizational_unit": "Pure Storage, Inc.",
  "state": "FL",
  "status": "self-signed",
  "valid_from": "2017-03-13T19:42:38Z",
  "valid_to": "2027-03-11T19:42:38Z"
}
```

11. Network Interface

View and set DNS and network interface attributes.

11.1 GET dns

Lists DNS attributes for the array administrative network.

Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

Example 1: List DNS settings

Request:

```
GET https://pure01.example.com/api/1.11/dns
```

Response:

```
{
  "domain": "example.com",
  "nameservers": [
    "192.168.0.1",
    "192.168.1.1"
  ]
}
```

11.2 PUT dns

Sets the DNS attributes for the array administrative network.

At least one parameter must be specified.

Parameters

| Parameter   | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|-------------|--------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| domain      | string | Domain suffix to be appended by the array when performing DNS lookups.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| nameservers | list   | A list of up to three DNS server IP addresses that replace the current list of name servers. For IPv4, specify the IP address in the form ddd.ddd.ddd.ddd, where ddd is a number ranging from 0 to 255 representing a group of 8 bits. For IPv6, specify the IP address in the form xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx, where xxxx is a hexadecimal number representing a group of 16 bits. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :). |

Optional.

**Example 1: Modify DNS settings**

Request:

```
PUT https://pure01.example.com/api/1.11/dns
{
  "domain": "example.com",
  "nameservers": [
    "192.168.1.1",
    "192.168.0.1"
  ]
}
```

Response:

```
{
  "domain": "example.com",
  "nameservers": [
    "192.168.0.1",
    "192.168.1.1"
  ]
}
```

**11.3 GET subnet**

Lists subnets and their statuses (enabled or disabled) and attributes.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List subnets**

Request:

```
GET https://pure01.example.com/api/1.11/subnet
```

Response:

```
[
  {
    "enabled": true,
    "gateway": null,
    "interfaces": [],
    "mtu": 1500,
    "name": "subnet100",
    "prefix": "192.168.0.0/24",
    "services": [],
    "vlan": 100
  }
]
```

**11.4 GET subnet/{subnet}**

Lists the attributes of the specified subnet.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List settings for subnet subnet100**

Request:

```
GET https://pure01.example.com/api/1.11/subnet/subnet100
```

Response:

```
{
  "enabled": true,
  "gateway": null,
  "interfaces": [],
  "mtu": 1500,
  "name": "subnet100",
  "prefix": "192.168.0.0/24",
  "services": [],
  "vlan": 100
}
```

**11.5 POST subnet/{subnet}**

Creates a subnet with the specified name.

At least one parameter must be specified.

**Parameters**

| Parameter | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|-----------|--------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| gateway   | string | Sets the IP address of the gateway through which the specified subnet is to communicate with the network. For IPv4, specify the gateway IP address in the form ddd . ddd . ddd . ddd. For IPv6, specify the gateway IP address in the form xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx / xxx. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :).<br><br>Optional.   |
| mtu       | number | Maximum message transfer unit (packet) size for the subnet in bytes. Valid values are integers between 1280 and 9216 (inclusive). The default value is 1500.<br><br>Optional.                                                                                                                                                                                                                                                                              |
| prefix    | string | Sets the IP address to be associated with the specified subnet. Specify the the subnet prefix and prefix length. For IPv4, specify the subnet prefix in the form ddd . ddd . ddd . ddd / dd. For IPv6, specify the subnet prefix in the form xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx / xxx. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :).<br><br>Optional. |
| vlan      | number | VLAN ID.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                  |

**Example 1: Create subnet mgmt with the specified gateway address and prefix**

Request:

```
POST https://pure01.example.com/api/1.11/subnet/mgmt
{
  "gateway": "192.168.100.1",
  "prefix": "192.168.100.0/24"
}
```

Response:

```
{
  "enabled": true,
  "gateway": "192.168.100.1",
  "interfaces": null,
}
```

```

"mtu": 1500,
"name": "mgmt",
"prefix": "192.168.100.0/24",
"services": null,
"vlan": null
}

```

## 11.6 PUT subnet/{subnet}

Modifies the attributes of the subnet.

At least one parameter must be specified.

### Parameters

| Parameter | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|-----------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| enabled   | boolean | Enables or disables a subnet.<br><br>Optional. Cannot be used with any other parameters.                                                                                                                                                                                                                                                                                                                                                                     |
| gateway   | string  | Sets the IP address of the gateway through which the specified subnet is to communicate with the network. For IPv4, specify the gateway IP address in the form ddd . ddd . ddd . ddd. For IPv6, specify the gateway IP address in the form xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx / xxx. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon ( : : ).<br><br>Optional.   |
| mtu       | number  | Maximum message transfer unit (packet) size for the subnet in bytes. Valid values are integers between 1280 and 9216 (inclusive). The default value is 1500.<br><br>Optional.                                                                                                                                                                                                                                                                                |
| name      | string  | Renames the specified subnet.<br><br>Optional. Cannot be used with any other parameters.                                                                                                                                                                                                                                                                                                                                                                     |
| prefix    | string  | Sets the IP address to be associated with the specified subnet. Specify the the subnet prefix and prefix length. For IPv4, specify the subnet prefix in the form ddd . ddd . ddd . ddd / dd. For IPv6, specify the subnet prefix in the form xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx : xxxx / xxx. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon ( : : ).<br><br>Optional. |
| vlan      | number  | VLAN ID.<br><br>Optional.                                                                                                                                                                                                                                                                                                                                                                                                                                    |

### Example 1: Change VLAN ID for subnet mgmt

Request:

```

PUT https://pure01.example.com/api/1.11/subnet/mgmt
{
  "vlan": 100
}

```

Response:

```

{
  "enabled": true,
  "gateway": "192.168.100.1",
  "interfaces": [],
  "mtu": 1500,
  "name": "mgmt",
  "prefix": "192.168.100.0/24",
  "services": [],
  "vlan": 100
}

```

**Example 2: Clear gateway for subnet mgmt**

Request:

```
PUT https://pure01.example.com/api/1.11/subnet/mgmt
{
  "gateway": null
}
```

Response:

```
{
  "enabled": true,
  "gateway": null,
  "interfaces": [],
  "mtu": 1500,
  "name": "mgmt",
  "prefix": "192.168.100.0/24",
  "services": [],
  "vlan": 100
}
```

**Example 3: Disable subnet mgmt**

Request:

```
PUT https://pure01.example.com/api/1.11/subnet/mgmt
{
  "enabled": false
}
```

Response:

```
{
  "enabled": false,
  "gateway": null,
  "interfaces": [],
  "mtu": 1500,
  "name": "mgmt",
  "prefix": "192.168.100.0/24",
  "services": [],
  "vlan": 100
}
```

**Example 4: Rename subnet mgmt**

Request:

```
PUT https://pure01.example.com/api/1.11/subnet/mgmt
{
  "name": "managementSubnet"
}
```

Response:

```
{
  "enabled": false,
  "gateway": null,
  "interfaces": [],
  "mtu": 1500,
  "name": "managementSubnet",
  "prefix": "192.168.100.0/24",
  "services": [],
  "vlan": 100
}
```

**11.7 DELETE subnet/{subnet}**

Deletes the specified subnet.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: Delete subnet managementSubnet**

Request:

```
DELETE https://pure01.example.com/api/1.11/subnet/managementSubnet
```

Response:

```
{
  "name": "managementSubnet"
}
```

**11.8 GET network**

Lists array administrative network interfaces and their statuses (enabled or disabled) and attributes.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List network interfaces**

Request:

```
GET https://pure01.example.com/api/1.11/network
```

Response:

```
[
  {
    "address": "10.14.227.30",
    "enabled": true,
    "gateway": "10.14.224.1",
    "hwaddr": "00:50:56:83:66:3c",
    "mtu": 1500,
    "name": "ct0.eth0",
    "netmask": "255.255.240.0",
    "services": [
      "management",
      "replication"
    ],
    "slaves": [],
    "speed": 10000000000,
    "subnet": null
  },
  {
    "address": null,
    "enabled": false,
    "gateway": null,
    "hwaddr": "00:50:56:83:15:c7",
    "mtu": 1500,
    "name": "ct0.eth1",
    "netmask": null,
    "speed": 10000000000,
    "subnet": null
  }
]
```

**11.9 GET network/{network\_component}**

Lists the attributes for the specified network component.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List settings for a single network interface**

Request:

```
GET https://pure01.example.com/api/1.11/network/ct0.eth0
```

Response:

```
{
  "address": "10.14.227.30",
  "enabled": true,
  "gateway": "10.14.224.1",
  "hwaddr": "00:50:56:83:66:3c",
  "mtu": 1500,
  "name": "ct0.eth0",
  "netmask": "255.255.240.0",
  "services": [
    "management",
    "replication"
  ],
  "slaves": [],
  "speed": 10000000000,
  "subnet": null
}
```

**11.10 POST network/vif/{vlan\_interface}**

Creates a VLAN interface.

**Parameters**

| Parameter | Type   | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
|-----------|--------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| address   | string | <p>Sets the IP address to be associated with the specified interface. The IP address must match the subnet prefix.</p> <p>For IPv4, enter the address in CIDR notation <code>ddd.ddd.ddd.ddd/dd</code>. For example, <code>10.20.20.210/24</code>. Alternatively, specify the address <code>ddd.ddd.ddd.ddd</code> with a netmask. The netmask is set through the <code>netmask</code> parameter.</p> <p>For IPv6, enter the address and prefix length in the form <code>xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx</code>. For example, <code>2001:0db8:85a3:ae26:8a2e:0370:7334/64</code>. Consecutive fields of zeros can be shortened by replacing the zeros with a double colon (<code>::</code>). Alternatively, specify the address <code>xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx</code> with a prefix length. The prefix length is set through the <code>netmask</code> parameter.</p> <p>Optional.</p> |
| subnet    | string | <p>Sets the subnet associated with the specified interface.</p> <p>Required.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |

**Example 1: Create a VLAN interface and associate it with subnet subnet100.**

Request:

```
POST https://pure01.example.com/api/1.11/network/vif/ct0.eth1.100
{
  "address": "192.168.0.100",
  "subnet": "subnet100"
}
```

}

Response:

```
{
  "address": "192.168.0.100",
  "enabled": true,
  "gateway": null,
  "hwaddr": "00:50:56:83:15:c7",
  "mtu": 1500,
  "name": "ct0.eth1.100",
  "netmask": "255.255.255.0",
  "services": [
    "iscsi"
  ],
  "slaves": [],
  "speed": 10000000000,
  "subnet": "subnet100"
}
```

### 11.11 PUT network/{network\_component}

Performs network interface actions and sets the administrative network component attributes.

At least one parameter must be specified.

#### Parameters

| Parameter    | Type    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
|--------------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| address      | string  | <p>Sets the IP address to be associated with the specified Ethernet interface.</p> <p>For IPv4, enter the address in CIDR notation ddd.ddd.ddd.ddd/dd. For example, 10.20.20.210/24. Alternatively, specify the address ddd.ddd.ddd.ddd with a netmask. The netmask is set through the netmask parameter.</p> <p>For IPv6, enter the address and prefix length in the form xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx. For example, 2001:0db8:85a3:ae26:8a2e:0370:7334/64. Consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :). Alternatively, specify the address xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx with a prefix length. The prefix length is set through the netmask parameter.</p> <p>Required if the netmask parameter is set.</p> |
| addslavelist | list    | <p>Add slaves to the existing list. May only be used on network bond interfaces.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| enabled      | boolean | <p>Enables (true) or disables (false) communication between the specified Ethernet interface and the administrative network. Do not disable the interface through which the administrative session is being conducted.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| gateway      | string  | <p>Sets the IP address of the gateway through which the specified interface is to communicate with the network. For IPv4, specify the gateway IP address in the form ddd.ddd.ddd.ddd. For IPv6, specify the gateway IP address in the form xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx. When specifying an IPv6 address, consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :).</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                             |
| mtu          | number  | <p>Maximum message transfer unit (packet) size for the interface in bytes. Valid values are integers between 1280 and 9216 (inclusive). The default value is 1500.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| netmask      | string  | <p>Used with the address parameter to define the range of IP addresses that make up a group of IP addresses on the same network. For IPv4, if the address is not entered in CIDR notation, enter the subnet mask in the form ddd.ddd.ddd.ddd. For example, 255.255.255.0. For IPv6, if the address entered does not include a</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                        |

prefix length, specify the prefix length. For example, 64.

Optional.

|              |        |                                                                                                 |
|--------------|--------|-------------------------------------------------------------------------------------------------|
| remslavelist | list   | Removes the list of slaves from the existing list. May only be used on network bond interfaces. |
|              |        | Optional.                                                                                       |
| slavelist    | list   | Replaces the existing slave list. May only be used on network bond interfaces.                  |
|              |        | Optional.                                                                                       |
| subnet       | string | Associates a subnet with the specified VLAN interface.                                          |
|              |        | Optional.                                                                                       |

#### Example 1: Disable network interface ct0.eth1

Request:

```
PUT https://pure01.example.com/api/1.11/network/ct0.eth1
{
  "enabled": false
}
```

Response:

```
{
  "address": null,
  "enabled": false,
  "gateway": null,
  "hwaddr": "00:50:56:83:15:c7",
  "mtu": 1500,
  "name": "ct0.eth1",
  "netmask": null,
  "services": [
    "iscsi"
  ],
  "slaves": [],
  "speed": 10000000000,
  "subnet": null
}
```

#### Example 2: Enable network interface ct0.eth1

Request:

```
PUT https://pure01.example.com/api/1.11/network/ct0.eth1
{
  "enabled": true
}
```

Response:

```
{
  "address": null,
  "enabled": true,
  "gateway": null,
  "hwaddr": "00:50:56:83:15:c7",
  "mtu": 1500,
  "name": "ct0.eth1",
  "netmask": null,
  "services": [
    "iscsi"
  ],
  "slaves": [],
  "speed": 10000000000,
  "subnet": null
}
```

### 11.12 DELETE network/{vlan\_interface}

Deletes a VLAN interface.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: Delete VLAN network interface ct0.eth1.100.**

Request:

```
DELETE https://pure01.example.com/api/1.11/network/ct0.eth1.100
```

Response:

```
{
  "name": "ct0.eth1.100"
}
```

**12. Hardware Components**

View and manage array hardware components.

**12.1 GET hardware**

Lists array hardware component information.

Returns information about array hardware components that are capable of reporting their status. The display is primarily useful for diagnosing hardware-related problems.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List all hardware devices**

Request:

```
GET https://pure01.example.com/api/1.11/hardware
```

Response:

```
[
  {
    "details": null,
    "identify": "off",
    "index": 0,
    "name": "CT0",
    "slot": null,
    "speed": null,
    "status": "ok",
    "temperature": null,
    "voltage": null
  },
  {
    "details": null,
    "identify": null,
    "index": 0,
    "name": "CT0.ETH0",
    "slot": 0,
    "speed": 10000000000,
    "status": "ok",
    "temperature": null,
    "voltage": null
  },
  {
    "details": null,
```

```
...
  "temperature": 25,
  "voltage": null
}
]
```

## 12.2 GET hardware/{component}

Lists the attributes for the specified hardware component.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

### Example 1: List a single hardware device

Request:

```
GET https://pure01.example.com/api/1.11/hardware/SH0.BAY0
```

Response:

```
{
  "details": null,
  "identify": "off",
  "index": 0,
  "name": "SH0.BAY0",
  "slot": null,
  "speed": null,
  "status": "ok",
  "temperature": null,
  "voltage": null
}
```

## 12.3 PUT hardware/{component}

Controls the visual identification of the specified chassis, controllers, flash module bays, NVRAM module bays, and storage shelves.

At least one parameter must be specified.

### Parameters

| Parameter | Type   | Description                                                                                                                                                                                                                                                                                             |
|-----------|--------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| identify  | string | Turns the LED light on or off to identify the specified component. Valid for chassis, controllers, flash module bays, NVRAM module bays, and storage shelves. Set identify to "on" to turn on the LED and identify the specified component. Set identify to "off" to turn off the LED.<br><br>Optional. |
| index     | string | Displays the specified number on the identifying component.<br><br>Optional.                                                                                                                                                                                                                            |

### Example 1: Turn on ID light for SH0.BAY0

Request:

```
PUT https://pure01.example.com/api/1.11/hardware/SH0.BAY0
{
  "identify": "on"
}
```

Response:

```
{
  "identify": "on",
  "index": 0,
  "name": "SH0.BAY0",
  "slot": null
}
```

Example 2: Turn off ID light

Request:

```
PUT https://pure01.example.com/api/1.11/hardware/SH0.BAY0
{
  "identify": "off"
}
```

Response:

```
{
  "identify": "off",
  "index": 0,
  "name": "SH0.BAY0",
  "slot": null
}
```

12.4 GET drive

Lists flash modules, NVRAM modules, and their attributes.

Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

Example 1: List all flash and NVRAM devices

Request:

```
GET https://pure01.example.com/api/1.11/drive
```

Response:

```
[
  {
    "capacity": 494927872,
    "details": null,
    "last_evac_completed": "1970-01-01T00:00:00Z",
    "last_failure": "1970-01-01T00:00:00Z",
    "name": "SH0.BAY0",
    "protocol": "SAS",
    "status": "healthy",
    "type": "SSD"
  },
  {
    "capacity": 494927872,
    "details": null,
    "last_evac_completed": "1970-01-01T00:00:00Z",
    "last_failure": "1970-01-01T00:00:00Z",
    "name": "SH0.BAY1",
    "protocol": "SAS",
    "status": "healthy",
    "type": "SSD"
  },
  {
    "capacity": 494927872,
    "details": null,
    "last_evac_completed": "1970-01-01T00:00:00Z",
    "status": "healthy",
    "type": "NVRAM"
  },
  ...
]
```

]

## 12.5 GET drive/{drive}

Lists the attributes for the specified flash module or NVRAM module.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

**Example 1: List a single flash module or NVRAM module.**

Request:

```
GET https://pure01.example.com/api/1.11/drive/SH0.BAY0
```

Response:

```
{
  "capacity": 494927872,
  "details": null,
  "last_evac_completed": "1970-01-01T00:00:00Z",
  "last_failure": "1970-01-01T00:00:00Z",
  "name": "SH0.BAY0",
  "protocol": "SAS",
  "status": "healthy",
  "type": "SSD"
}
```

## 13. Apps

View app attributes.

### 13.1 GET app

Lists the apps that are installed on the array, along with the attributes of each app.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 14. Users

View and manage users and directory service configurations.

### 14.1 GET admin

Lists public key and API token information for all users.

Set at least one parameter to true.

### Parameters

| Parameter | Type    | Description                                                                                                            |
|-----------|---------|------------------------------------------------------------------------------------------------------------------------|
| api_token | boolean | If set to true, displays a list of users that have REST API access and the dates in which the API tokens were created. |

Optional.

|           |         |                                                                                                                                                                                                 |
|-----------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| expose    | boolean | If <code>api_token</code> is set to <code>true</code> , set the <code>expose</code> parameter to <code>true</code> to unmask the current user's API token. Does not unmask other users' tokens. |
| Optional. |         |                                                                                                                                                                                                 |
| publickey | boolean | If set to <code>true</code> , displays a list of users that have public key access.                                                                                                             |
| Optional. |         |                                                                                                                                                                                                 |

**Example 1: List users who have public keys**

Request:

```
GET https://pure01.example.com/api/1.11/admin?publickey=true
```

Response:

```
[ ]
```

**Example 2: List users who have API tokens**

Request:

```
GET https://pure01.example.com/api/1.11/admin?api_token=true
```

Response:

```
[
  {
    "api_token": "*****",
    "created": "2017-03-13T19:40:32Z",
    "name": "os76"
  },
  {
    "api_token": "*****",
    "created": "2017-03-13T19:41:24Z",
    "name": "pureuser"
  }
]
```

**14.2 GET admin/{user}**

Lists public key information for the specified user.

**Parameters**

| Parameter | Type    | Description                                                                               |
|-----------|---------|-------------------------------------------------------------------------------------------|
| publickey | boolean | If set to <code>true</code> , displays the public key information for the specified user. |
| Required. |         |                                                                                           |

**14.3 GET admin/{user}/apitoken**

Lists the API token for the specified user.

**Parameters**

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 14.4 POST admin/{user}/apitoken

Creates an API token for the specified user.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 14.5 PUT admin

Clears all user permission cache entries.

User permission cache entries are also automatically updated when the user starts a new session.

### Parameters

| Parameter | Type    | Description                                                                                                 |
|-----------|---------|-------------------------------------------------------------------------------------------------------------|
| action    | string  | When set to refresh, refreshes all user permission cache entries.<br><br>Required.                          |
| clear     | boolean | When set to true, clears the entire user permission cache.<br><br>Required. Used with the action parameter. |

## 14.6 PUT admin/{user}

Sets the password or public key or refreshes the user permission cache entries for the specified user.

Either the publickey, password, or action parameter must be specified.

### Parameters

| Parameter    | Type    | Description                                                                                                                                                                                                                                                                                                                                                      |
|--------------|---------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action       | string  | When set to refresh, refreshes the user permission cache entries for the specified user.<br><br>Cache entries are also automatically updated when the user starts a new session.<br><br>Optional.                                                                                                                                                                |
| clear        | boolean | If the action parameter is set to "refresh", set the clear parameter to true to clear the user permission cache for the specified user.<br><br>Optional. Used with the action parameter.                                                                                                                                                                         |
| old_password | string  | Used with the password parameter to change the password for the single, local administrative account pureuser. Set the parameter to the old password.<br><br>Required if the password parameter is set.                                                                                                                                                          |
| password     | string  | Used with the old_password parameter to change the password for the single, local administrative account pureuser. The value must be between 1 and 32 characters in length and be entered from a standard English (U.S.) keyboard.<br><br>Optional.                                                                                                              |
| publickey    | string  | Changes the public key for SSH access for the specified user. Only system administrators can change public keys on behalf of other users. If no users are provided as arguments, a request to change the public key will be for the administrator issuing the request and a request to display set public keys will show all users with a public key configured. |

Optional.

## 14.7 DELETE admin/{user}/apitoken

Deletes API token for the specified user.

### Parameters

| Parameter | Type | Description |
|-----------|------|-------------|
| None      | n/a  | n/a         |

## 14.8 GET directoryservice

Lists current base configuration information for the directory service.

### Parameters

| Parameter   | Type    | Description                                                                                              |
|-------------|---------|----------------------------------------------------------------------------------------------------------|
| certificate | boolean | If set to true, returns information about the currently configured CA certificate data.<br><br>Optional. |
| groups      | boolean | If set to true, returns information about the group configuration.<br><br>Optional.                      |

### Example 1: List the directory service configuration

Request:

```
GET https://pure01.example.com/api/1.11/directoryservice
```

Response:

```
{
  "base_dn": "DC=ad1,DC=example,DC=com",
  "bind_password": "*****",
  "bind_user": "readonlyuser",
  "check_peer": false,
  "enabled": true,
  "uri": [
    "ldaps://ad1.example.com"
  ]
}
```

### Example 2: List the current configured CA certificate

Request:

```
GET https://pure01.example.com/api/1.11/directoryservice?certificate=true
```

Response:

```
{
  "certificate": "-----BEGIN CERTIFICATE-----
\nMIIE6jCCBF0gAwIBAgIDEIGKMA0GCSqGSIb3DQEBBQUAME4xCzAJBgNVBAYTA1VT\nnMRAwDgYDVQQKEwdFcXVpZmF4MS0wKwYDVQQLEyRFcXVp
ZmF4IFNlY3VyZSBkZXJ0\nawZpY2F0ZSBDbXR0b3JpdHkwHhcNMTAwNDAxMjMwMDE0wHcNMTUwNzAzMDQ1MDAw\nnWjCBjzEpMCcGA1UEBRMgMmc4
YU81d0kxYktKMlpENTg4VXNMdkRlM2duYmc4RFUx\nnCzAJBgNVBAYTA1VTMRMwEQYDVQQIEwpDYWxpZm9ybmlhMRIwEAYDVQQHEw1TdW5u\nneXZh
bGUxFDASBgNVBAoTC1lhaG9vICBjbMUMRYWFAVDVQDEw13d3cueWZob28u\nnY29tMIIBIjANBgkqhkiG9w0BAQEFAAOCQA8AMIIBCgKCAQEA6Z
M1jHCKL8rIEKse\n1ririTxyC3WvYQ5m34TlFK7dK4QFI/HPTtKGqQm3aVB1Fqi0aiTxe4YQMbd++jnkT\nndjxcpi7sJlFxfjMzs4umr1eGo2KgTgS
BAJyhxo23k+VpK1SprdPyM3yEfQVdV7JWC\nn4Y71CE2nE6+GbsIuhk/to+jJM07jXx/430jvo8vhNPL6Gvwe/D60bbnxS72ynLSd\nnmLtaltyk0v
ZEZiXbbfKgIaYymCgh89FGVvBkUbGM/Wb5Voiz7ttQLLxKOYRj8Mdk\nnTZtzPkM9scIFG1naECPvCw0NyMyxY3nF0djUKJ79twanmfCc1X2Z0/r
k1Cpi0uw\nnlrrr/QIDAQABo4ICDjCCAgowDgYDVR0PAQH/BAQDAgTwMB0GA1UdDgQWBBSmrFks\nn68m+dDUf+S7xJrQ/FXA1ZA6BgNVHR8EMZAx
```

```
MC+gLaArhilodHRwOi8vY3JsLmd1\nb3RydXN0LmNvbS9jcmxzL3NlY3VyZWZhLmNybDCCAVsGA1UdEQSCAVIwggF0gg13\nd3cuelFob28uY29tgg15YWhvby5jb22CDHVzLn1haG9vLmNvbYIMa3IueWFob28u\nY29tggx1ay55YWhvby5jb22CDG11Ln1haG9vLmNvbYIMZnIueWFob28uY29tggxp\nbi55YWhvby5jb22CDGNhLn1haG9vLmNvbYIMYnIueWFob28uY29tggxkZS55YWhv\nby5jb22CDGVzLn1haG9vLmNvbYIMbXguelFob28uY29tggxpdC55YWhvby5jb22C\nnDHNnLn1haG9vLmNvbYIMaWQuelFob28uY29tggxwaC55YWhvby5jb22CDHFjLn1h\nnaG9vLmNvbYIMdHcuelFob28uY29tggxoay55YWhvby5jb22CDGNuLn1haG9vLmNv\nnbYIMYXUueWFob28uY29tggxhc155YWhvby5jb22CDHZuLn1haG9vLmNvbTAFBgNV\nnHSMGDAWgBRI5mj5K9KylddH2CMgEE8zmJCf1DAdBgNVHSUEFjAUBgggBgEgFBQcD\n\nAQYIKwYBBQUHAWIwDQYJKoZIhvcNAQEFBQADgYEAp9WOMtcDMM5T0yPecGv5QhH\nnRJZRzgeMPZitLksr1JxxicJrdgv82Nwq1bw8aMuRj47ijrtaTEWxAcQCcy00yXodD\n\nnzoRJVNoYIvY1arYZf5zv9VZjN5I0HqUc39mNMe9XdZtbkWE+K6yVh60imKLbizna\nninu9YTrN/4P/w6KzHho=\n-----END CERTIFICATE-----"
```

### Example 3: List the directory service group configuration

Request:

```
GET https://pure01.example.com/api/1.11/directoryservice?groups=true
```

Response:

```
{
  "array_admin_group": "pureadmins",
  "group_base": "OU=PureStorage,OU=SAN,OU=IT,OU=US",
  "readonly_group": "purereadonly",
  "storage_admin_group": "pureusers"
}
```

## 14.9 PUT directoryservice

Modifies and tests the directory service configuration.

At least one parameter must be specified.

### Parameters

| Parameter         | Type    | Description                                                                                                                                                                                                                                                                                                                                                                      |
|-------------------|---------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| action            | string  | When set to test, tests the current directory service configuration; verifies that the URIs can be resolved and that Purity can bind and query the tree using the bind user credentials. The call also verifies that it can find all the configured groups to ensure the Common Names and group base are correctly configured.<br><br>Optional.                                  |
| array_admin_group | string  | Sets the common Name (CN) of the directory service group containing administrators with full privileges when managing the FlashArray. The name should be just the Common Name of the group without the CN= specifier. Common Names should not exceed 64 characters in length.<br><br>Optional.                                                                                   |
| auto_fetch        | boolean | When used with certificate, set the value to true to download and confirm the server certificate.<br><br>Optional.                                                                                                                                                                                                                                                               |
| base_dn           | string  | Sets the base of the Distinguished Name (DN) of the directory service groups. The base should consist of only Domain Components (DCs). The base_dn will populate with a default value when a URI is entered by parsing domain components from the URI. The base DN should specify DC= for each domain component and multiple DCs should be separated by commas.<br><br>Optional. |
| bind_password     | string  | Sets the password of the bind_user user name account.<br><br>Optional.                                                                                                                                                                                                                                                                                                           |
| bind_user         | string  | Sets the user name that can be used to bind to and query the directory.<br><br>For Active Directory, enter the username - often referred to as sAMAccountName or User Logon Name - of the account that is used to perform directory lookups.<br><br>For OpenLDAP, enter the full DN of the user.                                                                                 |

Optional.

|                     |         |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
|---------------------|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| certificate         | string  | <p>Certificate string in PEM format, including the "-----BEGIN CERTIFICATE-----" and "-----END CERTIFICATE-----" lines.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
| check_peer          | boolean | <p>Enables (true) or disables (false) server authenticity enforcement with the configured CA certificate.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| enabled             | boolean | <p>Enables (true) or disables (false) directory service support.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| group_base          | string  | <p>Specifies where the configured groups are located in the directory tree. This field consists of Organizational Units (OUs) that combine with the base DN attribute and the configured group CNs to complete the full Distinguished Name of the groups. The group base should specify OU= for each OU and multiple OUs should be separated by commas. The order of OUs is important and should get larger in scope from left to right. Each OU should not exceed 64 characters in length.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| readonly_group      | string  | <p>Sets the common Name (CN) of the configured directory service group containing users with read-only privileges on the FlashArray. This name should be just the Common Name of the group without the CN= specifier. Common Names should not exceed 64 characters in length.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| storage_admin_group | string  | <p>Sets the common Name (CN) of the configured directory service group containing administrators with storage-related privileges on the FlashArray. This name should be just the Common Name of the group without the CN= specifier. Common Names should not exceed 64 characters in length.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| trust               | boolean | <p>When used with certificate, set the value to true to skip certificate chain trust verification.</p> <p>Optional.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| uri                 | list    | <p>A list of up to 30 URIs of the directory servers. Each URI must include the scheme ldap:// or ldaps:// (for LDAP over SSL), a hostname, and a domain name or IP address. For example, ldap://ad.company.com configures the directory service with the hostname "ad" in the domain "company.com" while specifying the unencrypted LDAP protocol.</p> <p>If specifying a domain name, it should be resolvable by the configured DNS servers. If specifying an IP address, for IPv4, specify the IP address in the form ddd.ddd.ddd.ddd, where ddd is a number ranging from 0 to 255 representing a group of 8 bits. For IPv6, specify the IP address in the form [xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx], where xxxx is a hexadecimal number representing a group of 16 bits. Enclose the entire address in square brackets ([ ]). Consecutive fields of zeros can be shortened by replacing the zeros with a double colon (: :).</p> <p>If the scheme of the URIs is ldaps://, SSL is enabled. SSL is either enabled or disabled globally, so the scheme of all supplied URIs must be the same. They must also all have the same domain.</p> <p>If base DN is not configured and a URI is provided, the base DN will automatically default to the domain components of the URIs.</p> <p>Optionally specify a port. If a port number is specified, append it to the end of the address. Default ports are 389 for ldap, and 636 for ldaps. Non-standard ports can be specified in the URI if they are in use.</p> <p>Optional.</p> |

**Example 1: Disable the directory service**

Request:

```
PUT https://pure01.example.com/api/1.11/directoryservice
{
  "enabled": false
}
```

```
}

```

Response:

```
{
  "base_dn": "DC=ad1,DC=example,DC=com",
  "bind_password": "*****",
  "bind_user": "readonlyuser",
  "check_peer": false,
  "enabled": false,
  "uri": [
    "ldaps://ad1.example.com"
  ]
}
```

## Example 2: Enable the directory service

Request:

```
PUT https://pure01.example.com/api/1.11/directoryservice
{
  "enabled": true
}
```

Response:

```
{
  "base_dn": "DC=ad1,DC=example,DC=com",
  "bind_password": "*****",
  "bind_user": "readonlyuser",
  "check_peer": false,
  "enabled": true,
  "uri": [
    "ldaps://ad1.example.com"
  ]
}
```